


3-Phase Inverter Motor Drive Analysis

5 Series/5 Series B/6 Series B MSO Option 5-IMDA/6-IMDA Application Datasheet



Measurements and analysis on three-phase power systems are inherently more complex than on single-phase systems. Although oscilloscopes can capture voltage and current waveforms with high sample rates, further calculations are required to produce key power measurements from the data. The oscilloscope based three-phase solution allows to capture three-phase voltage and current waveforms with higher sample rates, longer record lengths using the HiRes acquisition mode that goes up to 16-bits and with the support of automated measurements produce key power test results. The Power converters based on Pulse Width Modulation (PWM), such as variable-frequency motor drives can complicate measurements since it is very important to extract precise zero crossings for the PWM signals, thus making an oscilloscope a recommended test tool for validation and troubleshooting for motor designers. Special software, designed to automate power analysis on inverters, motors, and drives, greatly simplifies important three-phase power measurements on PWM systems and can help engineers get faster insights into their designs. The Inverter Motor Drive Analysis (IMDA) solution from Tektronix helps engineers design better and more efficient three-phase motor drive systems, taking full advantage of the advanced user interface, six or eight analog input channels, and 'High Res' mode (16 bits) on the 5 Series/5 Series B/6 Series B MSO. The IMDA solution provides fast, accurate, and repeatable results for electrical measurements on industrial motors and drive systems for AC induction motors, permanent magnet synchronous motors (PMSM), and brushless DC (BLDC) motors. It can be configured to measure DC to three-phase AC converters, such as those used in the electric vehicles.

Key features and specifications

- Accurately analyze three-phase PWM signals used to drive AC induction, BLDC, and PMSM motors.
- Unique oscilloscope based phasor diagrams indicate V_{RMS} , I_{RMS} , V_{MAG} , I_{MAG} , and phase relationships at a glance for the configured wiring pairs.

- Debug motor drive designs by viewing the drive input/output voltage and current signals in the time domain simultaneously with the phasor diagram.
- Three-phase Autoset feature configures the oscilloscope for optimal horizontal, vertical, trigger, and acquisition parameters for acquiring three-phase signals.
- Measures three-phase harmonics per the IEC-61000-3-2, IEEE519-2014, and IEEE519-2022, or custom limits.
- Measures the system efficiency based on the selected wiring configurations.
- Quickly add and configure measurements through the intuitive drag and drop interface on the 5 Series/5 Series B/6 Series B MSO.
- Analyze Inverter and Automotive three-phase designs for DC input and AC output wiring configuration.
- Displays the PWM filtered edge qualifier waveform during analysis.
- Displays the test results per Record, or per Cycle mode during analysis for specific measurements.
- Supports Time trend and Acquisition trend plots for specific measurements.
- Supports mathematical conversion of Line-Line to Line-Neutral for specific wiring.
- Supports DQ0 measurements with the phasor plot and resultant vector navigation using oscilloscope cursors.
- Supports Angle measurement offset configuration for DQ0 measurement.
- Supports mechanical measurements and DQ0 using Hall sensors, QEI (Quadrature Encoder Interface), Resolvers, and Sine Cosine sensor signals with and without the Index pulse.
- Supports Torque measurement.
- Supports harmonic gating of all measurements by fundamental frequency and full spectrum.
- Computes the Mechanical power and System efficiency.

Measurement overview

Three-phase power converters such as variable frequency drives require a range of measurements during the design process. The Inverters, Motors, and Drives Analysis package for the 5 Series/5 Series B/6 Series B MSO automates key electrical measurements which are grouped into the Electrical Analysis group. The measurements can be configured to measure the Input or Output wiring configuration.




**Ihr Ansprechpartner /
Your Partner:**

dataTec AG

E-Mail: info@datatec.eu

>>> www.datatec.eu

Mess- und Prüftechnik. Die Experten.



IMDA measurements under Electrical Analysis group

The measurements can be set to measure 1V11 (1-Phase-2-Wire), 2V21 (1-Phase-3-Wire), 2V21 (3-Phase-3-Wire), 1V11 (1-Phase 2-Wire DC) or 3V31 (3-Phase-3-Wire), and 3P4W (3-Phase-4-Wire) to support various supply and motor configurations. Measurements can be performed line-to-line or line-to-neutral, to support delta and wye or star configurations.




Configuring the measurement for Input wiring configuration


Harmonics

Power waveforms are rarely textbook sinusoids. Harmonics measurements break down non-sinusoidal voltage or current waveforms into their sinusoidal components, indicating the frequency and amplitude for each component.

Harmonics analysis can be performed up to 200th harmonic order. The maximum harmonic order can be set to suit your needs by specifying the range in the measurement configuration. THD-F, THD-R, TDD and fundamental values are measured for each phase. Measurements can be evaluated against the IEEE 519-2014, IEEE 519-2022, or IEC 61000-3-2 standard, or custom limits. Test results can be recorded in a detailed report indicating pass/fail status.



Compare harmonics measurements against industry standards or custom limits



A sample harmonics plot indicates passing harmonics test results. Each set of bars contains results for Phase A, B, and C for easy correlation.

The Harmonics plot shows the test results for all three phases grouped together so user can correlate the test results between the phases. The plot also shows the test results visually. The harmonics bars are highlighted in green color


during a pass condition, and highlight to red color when it exceeds the test limits. This gives a quick insight when debugging for harmonics design.

Power Quality



This measurement provides critical three-phase power sub-measurements including: frequency and RMS magnitudes of voltage and current, crest factors of voltage and current, PWM frequency, and phase angle for each phase. It also displays the sum of true power, sum of reactive power, sum of apparent power components.

Additionally, in the Line-Neutral configuration, this measurement displays True Power, Reactive Power, and Apparent Power components of all the three-phases.

Voltage and current vectors can be displayed on a phasor diagram so you can quickly judge phase shift for each phase and the balance among phases. Each vector is represented by an RMS value and phase is computed using the Discrete Fourier Transform (DFT) method.




Easily configure the settings to get insight into the Power Quality



Easily configure the voltage and current inputs on the Power Quality measurement to display phasor diagrams

Method to compute Power Quality


The Power quality measurement can be configured to provide critical three-phase power measurements on the output side, including: frequency and RMS magnitudes of voltage and current, crest factors of voltage and current, PWM frequency, true power, reactive power, apparent power, power factor, and phase angle for each phase.




Unique oscilloscope based phasor diagram feature provides the relation between the voltage and current vectors

Ripple analysis

Ripple is defined as the residual or unwanted AC voltage on a constant DC component. It is typically measured on the DC bus. This measurement helps to understand how efficiently the signal is getting converted from AC-DC on the input side, and the impact of unwanted components on the PWM signal on the output side.



Ripple analysis configuration can be set to look into line and switching ripple



Ripple measurement being carried out on the DC-input signals when testing an Inverter

Direct Quadrature Zero (DQ0) analysis

The behavior of three-phase AC machines can be described by rotating voltage and current equations as below.

$$V_A = V_g \times \cos (w(t))$$

$$V_B = V_g \times \cos \left(\frac{w(t)-2\pi}{3} \right)$$

$$V_C = V_g \times \cos \left(\frac{w(t)-4\pi}{3} \right)$$

Where,

A, B, and C are three phase AC signals.

Vg is the corresponding gain.

w(t) is the 2pi*xt.

The voltages (V) and currents (I) at the AC interface are usually separated, typically 120 degrees out of phase. These V and I components are time-varying, which means there is no representation of a steady-state operation point.

Generally, AC signals are real-world signals, but converting them to DC helps get an abstract representation of the direct quadrature transform. The DQ0 assists in emulating the controller. This information helps to understand more about what the controller is doing and allows to tune the controller design.


The DQ0 transformations typically rotate the reference frames of AC waveforms to convert them to DC signals. This allows simplified calculations on the DC signals before performing the inverse transform to recover the actual three-phase AC results.

To measure and monitor the control system's output, the designers depend on FPGA's and ASIC-based hardware to handle sensor data to get the DQ0 information and then check the control information through multiple iterations. This solution involves a complex and time taking process.

It is practically challenging to measure or probe the D-Q-0 signals. A typical solution provides an external stimulus to the controller to replicate the controller input signals and the Analog-Digital Controller (ADC) outputs as the DQ0 signals.

To address this challenge, users depend on the software application DQ0 solution to understand the complex dynamic phenomena in power control systems.

The IMDA solution features DQ0 transformation, which rotates the reference frames of the three phase waveforms, so they become DC signals. Calculations can be simplified on these DC quantities before inverting them and getting to the actual three-phase AC results. A basic control scheme is shown in the following figure.



A basic control scheme for a permanent magnet synchronous motor

Typical connection setup and probing points for doing DQ0 measurements

Tektronix offers a patented measurement called DQ0 under the electrical analysis measurement category as an added option using Clarke's and Park's transformation matrix. The DQ0 feature is available as an option 5-IMDA-DQ0/6-IMDA-DQ0 on the 5 Series, 5 Series B, and 6 Series B MSO.


The DQ0 method calculates the angle (θ) as $2\pi \cdot \text{int}(\omega_m \cdot t)$ and extrapolates the reference frame based on where we expect time-varying signals to be. The DQ0 frame (phasor diagram) rotates with the right speed and frequency and not necessarily in phase with the rotor, which helps to understand the instantaneous state of the motor.

This measurement is supported in the 3V3I configuration, takes the three-phase voltage or current signals from the motor as inputs, and converts them into D-Q-0 coefficients acting as a powerful debugging tool for the motor designers to tune their PWM controller circuit designs.


The measurement computes real-time DQ0 transformation by converting the 3-phase drive output voltage or current waveforms. The transform matrix converts time-varying AC signals into time-invariant DC components. This helps to reproduce the control system's understanding of instantaneous motor torque and speed. The use of the DQ0 transformation allows motor designers to correlate the performance of the 3Phase power section to control system of the hardware algorithms and design. The overlapped DQ0 and 3-phase ABC vectors act as a good debug feature for designers to observe simultaneously both vector axis on the same plot.

There are different outputs of this measurement such as scalar values with the magnitude of D and Q, RMS values with statistics, derived math waveforms, and a phasor diagram. Math waveform provides the DC transformed waveform. This provides the different views of the control system outputs in a single view.

By observing the DQ0 results, some important inferences can be drawn, such as variations indicating to RMS ripple, peak to peak values, and higher-order harmonics. These parameters directly relate to understanding the operation of the algorithms in the control systems. Without this information, it would be difficult to understand the performance of the motor control systems.



DQ0 with QE1 configuration




DQ0 offset configuration

Configure the offset (electrical) angle:


- To adjust if there is any position misalignment of the mounted encoder/ sensors.
- If there is any low pass filter delay after applying the filter on the electrical signals.

This is also supported with and without sensors configuration. If analog sources are configured for electrical measurement and digital sources for mechanical measurement then enter the low pass filter phase delay and position misalignment combined as an offset angle.



DQ0 measurement running on the 5 Series MSO. They are represented on the phasor diagram as Q (green), D(orange), and Z (white) vectors and their scalar values are available in the results badge on the right. The DQ0 waveforms are shown as Math M1, Direct (purple), Quadrature (red), and Zero (green).

The enhanced DQ0 algorithm computes the resultant vector from the D and Q components and displays a resultant vector as an overlapped motor rotations, and integrated with instantaneous motor angle (theta).



The DQ0 plot displays the resultant as rotating persistence plot.


Dynamic measurements using trend analysis

A common requirement in motor drive analysis is an ability to look at the motor response over longer test times, records, and an extended number of acquisitions to monitor the DUT behavior over varying load conditions. This dynamic measurement helps to understand optimal designs and interdependency between different parameters like voltage, current, power, frequency, and their variance based on the load conditions. You can manually zoom and get the specific region of interest to look at test results at the particular region of the waveform.


IMDA solution offers two unique trend plots on the power quality measurement to support such requirements:

- Time trend plot
- Acq trend plot

Each plot has its advantages and can be used to plot the supported sub-measurements under power quality measurement. The time trend plot shows the measured value per cycle, or for an acquired waveform (a record), while the acq trend plot shows a mean of the measured value per record, over each of the acquisitions. The acquisition count can be set during the test configuration. This allows you to capture long records of data to perform deep record analysis and understand the dynamic behaviors of the motor response. The plots can be saved as a CSV file for post-processing.



Time trends enable you to graphically analyze power measurements within one acquisition record. Acquisition trends can plot power measurements over many acquisitions for longer-term testing.



This example shows acquisition trend plots of mean power measurements for 100 acquisitions, including - Vrms, Irms, phase difference, sum of true power, apparent power, and reactive power.




Add and configure the Time Trend plot on different sub-measurements of Power Quality measurement. The image shows two time-trend plots monitoring Vrms and Frequency parameters.

Mechanical analysis

The IMDA mechanical analysis group (Option IMDA-MECH) supports Hall sensor, QEI, Resolver, and Sine Cosine output signals to calculate speed, acceleration, and direction information. In addition to these measurements, the QEI method also supports the angle measurement and displays them in degrees or radians. The acceleration results are reported as part of the speed measurement. The measurement requires the number of pole pairs and corresponding gear ratio to measure key motor parameters. The direction measurement expects a sequence of hall sensor rising edges to be configured before operation and validates them during the operation. For the QEI method, the measurement requires the information on QEI outputs - Phase-A, Phase-B, the optional Z-index pulse, and Pulses per Rotation (PPR).


The TPP1000 passive probes or high voltage differential THDP0200/100 probes can be used to capture the sensor outputs depending on the motor output power and noise levels. Digital channels with TLP logic probes are recommended for use instead of analog because of lesser noise and can help to conserve analog channels for other tests operations and use single flex channel for the measurement.



IMDA mechanical analysis supports speed (with acceleration) and direction measurements

Speed measurement

Hall sensor signal transition as shown in the following figure.



Speed measurement computation using three hall sensor transitions

Speed is defined by the following equation,

$$Speed \text{ in RPM} = \left(\left(\frac{1}{T_{SP} - T_{ST}} \right) * 60 \right) * G$$

Where,

Difference between T_{SP} and T_{ST} is defined by the number of pole pairs.

T_{ST} is the start of the electrical pulse

T_{SP} is the stop of the electrical pulse

60 is the RPM (revolutions per minute)

G is the gear ratio.

Speed measurement can be calculated either once per rotation or for every QEI sensor signal cycle.

Acceleration measurement

Acceleration is rate of change of speed per unit time. It is defined as

$$Accr = \frac{Speed(t_{n+1}) - Speed(t_n)}{((t_{n+1}) - t_n)}$$

Speed and direction support following plots:


- Histogram
- Time Trend
- ACQ Trend



Measuring motor speed and direction using QEI method. The QEI signals (Phase A, B, and Z index) are shown for reference by connecting both Analog (TPP1000) and Digital (TLP058) probes.

Importance of speed ACQ trend plots

The ACQ trend along with the histogram plot shows jitter on motor speed, which otherwise requires dedicated instrument like a flutter meter to measure. This jitter information (variations in edge timing) measures the motor-speed consistency.




ACQ trend plot displaying jitter on the motor speed (left) along with a histogram plot (right) that indicates the speed distribution

Motor start-up profile

Motor designers are interested to investigate the motor startup profile during the design stage. The time trend gives the instantaneous speed information of a motor which otherwise is hard to measure.

In the following *Time trend plot showing startup sequence of a motor image*, where the start-up time taken by the motor is 2.3s from OFF to a ON state. Similarly, one can perform ON to OFF state and gain insights into the de-acceleration process as shown in the figure *Time trend plot showing deceleration of a motor into a stop state image*.



Time trend plot displaying start-up sequence of a motor




Time trend plot displaying deceleration of a motor into a stop state


Direction measurement

Some applications like drills, washing machines, and electric pumps require motor to operate and change directions rapidly. The direction measurement helps with this analysis. The order of rising edges or falling edges of hall sensor output determines the direction of rotation. The direction measurement needs all three hall signals. They are available as configurable parameters for the direction measurement and are validated during the motor operation. Generally, a A-B-C sequence is interpreted as clockwise (CW) and a A-C-B sequence is interpreted as counter-clockwise (CCW).

For example, if the first rising edge is from HALL A and a rising edge of HALL B exists at 120 degrees, then the rotor rotation sequence is A-B-C. Else, if the second rising edge of HALL C occurs at 120 degrees, then the sequence is A-C-B.



Direction information interpreted from the Hall sensor outputs



Direction information captured on the scope shows a HALL A,B,C rising edge sequence (clockwise rotation)


Here is the formula used to compute the direction information.

Order (Clockwise) = (A-B-C)

Order (Counter-clockwise) = (A-C-B)

Where Order function checks for the sequence of rising edges on all three hall sensor signals.

Direction can be displayed as an ACQ trend plot to give a visual indication on an exact timestamp when the motor reversed the direction helping during the debug. This is shown as a sample plot in the following figure.



The ACQ trend plot shows +1 and -1 based on CW and CCW motor rotation.

Resolvers

Resolver is a sensor that is mounted on a motor to determine the angular position of the rotor.

A resolver produces three signal outputs, Excitation - used as a reference, Sine, and Cosine used for analysis. The Sine and Cosine signals are orthogonal to each other and are modulated with the reference signal. The Sine and Cosine envelopes are extracted before measuring the various parameters.

Following measurements are available with resolver support:


- The instantaneous angle is measured by:

$$\text{Angle} = \arctan(\sin \text{ value} / \cos \text{ value})$$

- The formula for computing Speed is

$$\text{Speed} = [\text{Frequency}(\text{envelope signal}) / \text{Pole pairs}] \text{ Hz}$$

Where envelope signal is the output of the envelope extraction.



Sine Cosine Sensor

A Sine Cosine sensor is a precision angular position sensor that provides two orthogonal sinusoidal output signals with a 90-degree phase relationship. Unlike a Hall sensor, which delivers discrete digital transitions, or a QEI encoder, which generates pulse trains, a Sine Cosine sensor delivers continuous analog signals. These signals enable smooth, high-resolution position measurement.

The sensor consists of a rotating element (typically magnetic or optical) that produces two sinusoidal output signals as it rotates.

Both speed and angle measurements are supported by the Sine Cosine sensor.

- Speed is derived from the frequency of the sine envelope signal.


$$\text{Speed (Hz)} = \frac{\text{Frequency of Sine}}{\text{Cycles Per Rotation}} \times \text{Gear Ratio}$$

$$\text{Speed (RPM)} = \text{Speed (Hz)} * 60$$

- The instantaneous mechanical angle is calculated using the arctangent of the ratio of the sine and cosine signals.

$$\text{Angle} = \tan^{-1} \left(\frac{\text{Sin value}}{\text{Cos value}} \right)$$

The direction of the rotation is determined by analyzing the phase relationship between consecutive angle measurements. The algorithm uses robust slope detection over a sliding window to minimize the noise effects and provide reliable direction indication.



Configuration options for Speed measurement with Sine Cosine sensor

Torque measurement

The torque of a motor is the rotary force produced on its output shaft, it is a twisting force that is measured in Newton-meters (Nm).

IMDA supports two methods for torque measurements:

- Sensor method:**

This is the most common torque measurement that uses the torque sensor or the Load cell output. Measuring the torque generated by motors can be done by coupling a rotary torque sensor in line with the motor shaft. Users can capture Torque waveform using a passive voltage probe. The voltage waveform is proportional to a measured torque value.

The user must configure high and low values of the Torque sensor and corresponding high and low values of the output voltage. The measurement rescales the acquired voltage waveform to the Torque values.

The Load cell provides the Force. The Torque value is computed as a product of force and the arm length (distance).

$$\text{Torque Output} = \text{Voltage Input} \times \frac{\text{High Torque} - \text{Low Torque}}{\text{High Voltage} - \text{Low Voltage}}$$

2. Current method:

Many motors have data specifications by which torque can be inferred as proportional to applied RMS current by using the Torque constant. This is an estimation of the torque value.

Generally, the torque developed in any dc motor is proportional to the torque constant times the armature current. In a series motor, the field current is proportional to the armature current.

The torque produced by the rotor is estimated to be directly proportional to the armature current. The user must configure the Torque constant of the motor.


Torque = Torque constant x I_{rms}

The torque measurement supports the following plots:


- Histogram
- Time Trend
- ACQ trend.

Following torque units are part of the configuration:


- Newton Meters (N·m)
- Foot pounds (ft·lb)
- Inch ounces (in·oz)
- Inch pounds (in·lb).




Torque measurement setup using the armature current method



The image shows torque results as an ACQ trend plot using a Load cell output.



Torque measurement setup using the torque sensor method



The image shows torque results as a histogram plot using a torque constant and armature current output

Mechanical Power measurement

The Mechanical Power of a rotating shaft is determined by its speed of rotation and the torque that it provides. This measurement supports Hall Sensors QEI encoder, and Sine Cosine sensor to compute Speed and Torque.

The Mechanical Power measurement computes torque using either a torque sensor or an armature current input, and speed using hall or QEI sensor inputs.

The computed Mechanical power using these inputs are directly proportional to the product of speed and torque of the shaft.


IMDA supports different sensor types to measure torque, speed, and angular position of the motor.

$$\text{Mechanical Power} = (\text{Torque} \times \text{Multiplier}) \times \text{Speed}$$


Where the Multiplier is based on the torque unit and it can be 104.7252 nm, 0.739522 oz-inch, 141.9883 ft-lb, or 11.83235897 inch-lb.

Speed is in RPM.

Mechanical Power is in Watt.



Typical motor setup for computing System Efficiency and Mechanical Power



Configuration options for Mechanical Power measurement

System Efficiency measurement

System Efficiency is the measure of the effectiveness with which electrical energy is converted to mechanical energy. This measurement is often performed at different speeds under different loads and is commonly displayed as a speed torque curve.

Power efficiency is a measure by which all the electrical equipment is rated, so it is important to measure it dynamically to check whether the motor is operating in the desired region.

The IMDA System Efficiency measurement takes in electrical voltage and current inputs to compute the input power and torque and speed sensors signal to compute the output mechanical power. Based on these parameters, system efficiency is computed. The electrical power can be computed using 2V2I or 3V3I wiring based on the oscilloscope channels available.

For an electrically driven motor, the output power is mechanical while the input power is electrical, so the efficiency equation is computed by

$$\text{System Efficiency} = ((\text{Output mechanical power}) / (\text{Input electrical power})) \times 100\%$$

Report generation

The IMDA software simplifies data collection, archiving, documentation of your design, and development process. It supports the report generation in MHT or PDF formats with pass/fail results for easy analysis.

Measurement Report Teltronix Monday February 3 2020 10:54:56

Setup Configuration


Scope Details			
Scope Model Number	Scope Serial Number	TekScope Version	Scope Calibration Status
MSO58	Q100118	1.24.6	Pass

IMDA High Level Configuration

Measurement Type	Wiring	Connection	L-L to L-N
Industrial	3 Phase-3 Wire (3V3)	Line-to-Line	False

Name	Measurement Src(s)	Mean'	Min'	Max'	Pk-Pk'	Std Dev'	Population'	Accum Mean	Accum Min	Accum Max	Accum Pk-Pk'	Accum Std Dev'	Accum Pop
IMDA Meas 1 - Power Quality	Ch 1, Ch 2 - Phase 1 (Vrms, Ia)	375.12 V	375.12 V	375.12 V	0.0000 V	0.0000 V	1	375.12 V	375.12 V	375.12 V	0.0000 V	0.0000 V	1
VRMS		330.21 mA	330.21 mA	330.21 mA	0.0000 A	0.0000 A	1	330.21 mA	330.21 mA	330.21 mA	0.0000 A	0.0000 A	1
IRMS		1.7386	1.7386	1.7386	0.0000	0.0000	1	1.7386	1.7386	1.7386	0.0000	0.0000	1
Voltage Crest Factor		3.0543	3.0543	3.0543	0.0000	0.0000	1	3.0543	3.0543	3.0543	0.0000	0.0000	1
Current Crest Factor		83.258 W	83.258 W	83.258 W	0.0000 W	0.0000 W	1	83.258 W	83.258 W	83.258 W	0.0000 W	0.0000 W	1
True Power		-91.713 VAR	-91.713 VAR	-91.713 VAR	0.0000 VAR	0.0000 VAR	1	-91.713 VAR	-91.713 VAR	-91.713 VAR	0.0000 VAR	0.0000 VAR	1
Reactive Power		123.87 VA	123.87 VA	123.87 VA	0.0000 VA	0.0000 VA	1	123.87 VA	123.87 VA	123.87 VA	0.0000 VA	0.0000 VA	1
Apparent Power		980.75 m	980.75 m	980.75 m	0.0000	0.0000	1	980.75 m	980.75 m	980.75 m	0.0000	0.0000	1
Power Factor		-11.260	-11.260	-11.260	0.0000	0.0000	1	-11.260	-11.260	-11.260	0.0000	0.0000	1
Phase Angle		0.0000	0.0000	0.0000	0.0000	0.0000	1	0.0000	0.0000	0.0000	0.0000	0.0000	1
V Phase		-11.260	-11.260	-11.260	0.0000	0.0000	1	-11.260	-11.260	-11.260	0.0000	0.0000	1
I Phase		0.0000	0.0000	0.0000	0.0000	0.0000	1	0.0000	0.0000	0.0000	0.0000	0.0000	1

Views



Global Configuration

Setting	Jitter Separation Model	Dual Dirac Model	Display Unit Type	Standard Reference Levels	Jitter Reference Levels	Lock RJ
None	SpectralOnly	FitExpress	Seconds	Every Acquisition	First Acquisition	None

Reference Levels Configuration

Ref Levels	Ch1, Ch2, Ch3, Ch4, Ch5, Ch6
Ref Level Type	Global
Base Top Method	MinMax
RiseHigh	90%
RiseMid	50%
RiseLow	10%
FallHigh	90%
FallMid	50%
FallLow	10%
Hysteresis	10%

A sample IMDA test report file with summary, details, and corresponding images

Specifications

Wiring configuration	1V1I (1-Phase-2Wire), 2V2I (1 Phase-3-Wire), 2V2I (3-Phase-3-Wire), 2V2I (DC In-AC Out), 3V3I (DC In-AC Out) or 3V3I (3-Phase-3Wire), and 3P4W (3-Phase-4Wire)
L-L to L-N conversion	Applicable for 3 Phase-3 Wire (3V3I) ¹
Electrical analysis	Power quality, Harmonics ² , Ripple, DQ0 ³ , Efficiency ⁴
Sensors supported	Hall sensors, Resolvers, QEI (Quadrature Encoder Interface), and Sine Cosine sensor
Mechanical analysis	Speed, Acceleration, Angle (QEI method), Direction, Torque, Mechanical Power, and System Efficiency
Harmonic gating	Fundamental and full spectrum
Three-phase autose	For all measurements
Plots	Time Trend plot, ACQ trend plot, Phasor diagram, harmonics bar graph ⁵ , DQ0 plot, and Histogram plot (speed distribution)
Report	MHT and PDF format, Data export to CSV format
Degauss/Deskew (static)	Automatic detection of probes, Auto Zero. User can deskew voltage and current probes, degauss the current probe from the menus for each channel
Source support	Live analog signals, reference waveforms, and math waveforms

¹ For 3 Phase-4 Wire (3V3I) the connection is always Line to Neutral and for 3 Phase-3 Wire (2V2I), it is Line to Line.

² Supports custom limits.

³ Applicable for 3V3I wiring only.

⁴ For 2V2I wiring only.

⁵ Range filter as part of measurement configuration.

Ordering information

Models

Product	Options ⁶	Supported instruments	Bandwidth available
New instrument order option	5-IMDA	5 Series MSO (MSO56, MSO58)	<ul style="list-style-type: none"> • 350 MHz • 500 MHz • 1 GHz • 2 GHz
Product upgrade option	SUP5-IMDA	5 Series B MSO (MSO56B, MSO58B)	
Floating license	SUP5-IMDA-FL	MSO58LP	
New instrument order option	5-IMDA-DQ0		
Product upgrade option	SUP5-IMDA-DQ0		
Floating license	SUP5-IMDA-DQ0-FL		
New instrument order option	5-IMDA-MECH		
Product upgrade option	SUP5-IMDA-MECH		
Floating license	SUP5-IMDA-MECH-FL		
New instrument order option	6-IMDA	6 Series B MSO (MSO66B, MSO68B)	<ul style="list-style-type: none"> • 1 GHz • 2.5 GHz • 4 GHz • 6 GHz • 8 GHz • 10 GHz
Product upgrade option	SUP6B-IMDA		
Floating license	SUP6B-IMDA-FL		
New instrument order option	6-IMDA-DQ0		
Product upgrade option	SUP6B-IMDA-DQ0		
Floating license	SUP6B-IMDA-DQ0-FL		
New instrument order option	6-IMDA-MECH		
Product upgrade option	SUP6B-IMDA-MECH		
Floating license	SUP6B-IMDA-MECH-FL		

⁶ Options IMDA-DQ0 and IMDA-MECH requires Option IMDA as a pre-requisite

Software bundles

Supported instruments	Bundle options	Description
5 Series/5 Series B MSO	5-PRO-POWER-1Y	1 Year License Pro Power Bundle
	5-PRO-POWER-PER	Perpetual License Pro Power Bundle
	5-ULTIMATE-1Y	1 Year License Ultimate Bundle
	5-ULTIMATE-PER	Perpetual License Ultimate Bundle
	5-PRO-AUTO-1Y	1 Year License Pro Automotive Bundle
	5-PRO-AUTO-PER	Perpetual License Pro Automotive Bundle
6 Series B MSO	6-PRO-POWER-1Y	1 Year License Pro Power Bundle
	6-PRO-POWER-PER	Perpetual License Pro Power Bundle
	6-ULTIMATE-1Y	1 Year License Ultimate Bundle
	6-ULTIMATE-PER	Perpetual License Ultimate Bundle
	6-PRO-AUTO-1Y	1 Year License Pro Automotive Bundle
	6-PRO-AUTO-PER	Perpetual License Pro Automotive Bundle

Recommended probes

Probe model	Description	Quantity
TCP0030A or TCP0150	Current Probes	3 for 3V3I wiring ⁷
THDP0200 or TMDP0200	High Voltage Differential Probes	3 for 3V3I wiring ⁷

Tektronix is registered to ISO 9001:2015 and ISO 14001:2015.

⁷ For performing efficiency measurement, four quantities are required.

ASEAN / Australasia (65) 6356 3900
 Belgium 00800 2255 4835*
 Central East Europe and the Baltics +41 52 675 3777
 Finland +41 52 675 3777
 Hong Kong 400 820 5835
 Japan 81 (120) 441 046
 Middle East, Asia, and North Africa +41 52 675 3777
 People's Republic of China 400 820 5835
 Republic of Korea +82 2 565 1455
 Spain 00800 2255 4835*
 Taiwan 886 (2) 2656 6688

Austria 00800 2255 4835*
 Brazil +55 (11) 3759 7627
 Central Europe & Greece +41 52 675 3777
 France 00800 2255 4835*
 India 000 800 650 1835
 Luxembourg +41 52 675 3777
 The Netherlands 00800 2255 4835*
 Poland +41 52 675 3777
 Russia & CIS +7 (495) 6647564
 Sweden 00800 2255 4835*
 United Kingdom & Ireland 00800 2255 4835*

Balkans, Israel, South Africa and other ISE Countries +41 52 675 3777
 Canada 1 800 833 9200
 Denmark +45 80 88 1401
 Germany 00800 2255 4835*
 Italy 00800 2255 4835*
 Mexico, Central/South America & Caribbean 52 (55) 56 04 50 90
 Norway 800 16098
 Portugal 80 08 12370
 South Africa +41 52 675 3777
 Switzerland 00800 2255 4835*
 USA 1 800 833 9200

* European toll-free number. If not accessible, call: +41 52 675 3777

For Further Information. Tektronix maintains a comprehensive, constantly expanding collection of application notes, technical briefs and other resources to help engineers working on the cutting edge of technology. Please visit www.tek.com.

Copyright © Tektronix, Inc. All rights reserved. Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supersedes that in all previously published material. Specification and price change privileges reserved. TEKTRONIX and TEK are registered trademarks of Tektronix, Inc. All other trade names referenced are the service marks, trademarks, or registered trademarks of their respective companies.

7 Jan 2026 48W-61649-8



**Ihr Ansprechpartner /
Your Partner:**

dataTec AG
 E-Mail: info@datatec.eu
 >>> www.datatec.eu

Mess- und Prüftechnik. Die Experten.

