

**3GHz SPECTRUM ANALYZER**

**GSP-9300B**



**PRACTICAL, AFFORDABLE AND NEVER CARELESS!**

GSP-9300B is a 3GHz spectrum analyzer to meet basic RF measurement requirements. It provides the frequency stability of 0.025ppm; the aging rate of 1ppm/year; a built-in preamplifier; the base noise of -149dBm/Hz, and more than 20 measurement applications, including AM/FM modulation signal analysis, signal channel analysis, and CATV parameter test. While collocating with TG option, GSP-9300B can conduct frequency response or power linearity tests for components.

For monitoring signals, GSP-9300B provides Topographic display mode, which is capable of distinguishing continuous or random signals by using color temperature. Spectrogram mode provides a time axis on spectrum display that allows users to observe signal variations based upon the reference of time. Split window mode allows different parameter settings for each display window. Additionally, GSP-9300B also provides user-friendly user interfaces such as display mode, help, multi-languages, and fast data logging, etc. Interfaces and software include USB/RS-232/LXI/MicroSD/GPIB (option)/DVI output and dedicated PC software IVI Driver.

GSP-9300B, with its unique features, including auto wake-Up, sequence function, and limit line testing, is specially designed to meet the requirements of production lines. The patent design of heat conduction allows GSP-9300B to substantially reduce the warm-up time so as to expedite production processes. Options include tracking generator, carrying bag, battery module, EMI antenna set and rack accessories. The compact design of GSP-9300B satisfies either field testing or the integration of automatic testing systems.

To sum up, GSP-9300B is a stable, light and all-purpose test equipment, which is the most ideal choice for the educational market, production line, and general signal monitoring applications, etc. Most important, the pricing of GSP-9300B is beyond your imagination and it is the number one choice for users with budget considerations.

**Frequency Stability : 0.025ppm**

Wireless communications applications are nowadays ubiquitous. Signals in the limited spectrum are getting very crowded. Therefore, the demands of signal efficiency and frequency stability are higher and stricter. To meet high precision measurement requirements, GSP-9300B provides the frequency stability of 0.025ppm and the aging rate of 1ppm/year, which only appear in high-end T&M equipment.

**Built-in Preamplifier**

Engineers often face the challenge of measuring small RF signals during product development stage. GSP-9300B's built-in preamplifier provides the base noise of -149dBm. When collocating with the built-in EMI filter and the dedicated EMI near field probe, GSP-9300B can conduct EMI tests and debugging.

**More Than 20 Measurement Applications**

GSP-9300B provides rich signal processing functions, including AM/FM modulation signal analysis, signal channel analysis, and CATV parameter test, characteristic test on signal stability, and frequency response or power linearity tests for components to substantially bring up the measurement convenience. Most competitors in the same class only offer a few test functions, and the standard built-in functions of GSP-9300B are options for competitors.

## FEATURES

- Frequency Range : 9kHz ~ 3 GHz
- 0.025ppm Frequency Stability and 1ppm Aging Rate
- Built-in Preamp, 50dB Attenuator, and Sequence Function
- RBW : 1Hz ~ 1MHz
- Sensitivity : -149dBm/Hz (@PreAmp on)
- Built-in AM/FM Demodulation & Analysis
- Built-in P1dB point, Harmonic, Channel Power, N-dB Bandwidth, OCBW, ACPR, SEM, TOI, CNR, CTB, CSO, Noise Marker, Frequency Counter, Time Domain Power, Gated Sweep
- Built-in Spectrogram, Topographic and Dual-View Display Modes
- Remote Control Interface : LAN, USB, RS-232
- Options : Tracking Generator, GPIB Interface

## APPLICATIONS

- For the Quick Check and Analysis of Spectral Characteristic
- Analyze AM, FM Signal Characteristics
- Monitor Satellite Uplink Signals From Satellite Uplink Truck
- Test Systems That Require a Very Compact Instrument
- Measure The Frequency Response of Cable, Attenuator, Filter and Amplifier

## SPECIFICATIONS

### FREQUENCY

#### FREQUENCY

Range	9 kHz ~ 3 GHz	
Resolution	1 Hz	

#### FREQUENCY REFERENCE

Accuracy	$\pm$ (period since last adjustment x aging rate) + stability over temperature + supply voltage stability	1 year after last adjustment
Aging Rate	$\pm$ 1 ppm max.	0 ~ 50 °C
Frequency Stability Over Temperature	$\pm$ 0.025 ppm	
Supply Voltage Stability	$\pm$ 0.02 ppm	

#### FREQUENCY READOUT ACCURACY

Start, Stop, Center, Marker	$\pm$ (marker frequency indication x frequency reference accuracy + 10% x RBW + frequency resolution)	
Trace Points	Max. 601 points, Min. 6 points	

#### MARKER FREQUENCY COUNTER

Resolution	1 Hz, 10 Hz, 100 Hz, 1 kHz	
Accuracy	$\pm$ (marker frequency indication X frequency reference accuracy + counter resolution)	RBW/Span $\geq$ 0.02 ; Mkr level to DNL>30 dB

#### FREQUENCY SPAN

Range	0 Hz (zero span), 100 Hz ~ 3 GHz	
Resolution	1 Hz	
Accuracy	$\pm$ frequency resolution	RBW : Auto

#### PHASE NOISE

Offset from Carrier		$F_c=1\text{GHz}; \text{RBW}=1\text{kHz}; \text{VBW}=10\text{Hz}; \text{Average} \geq 40$
10 kHz	< -88 dBc/Hz	Typical
100 kHz	< -95 dBc/Hz	Typical
1 MHz	< -113 dBc/Hz	Typical

#### RESOLUTION BANDWIDTH (RBW) FILTER

Filter Bandwidth	1 Hz ~ 1 MHz in 1-3-10 sequence	-3dB bandwidth
Accuracy	200 Hz, 9 kHz, 120 kHz, 1 MHz	-6dB bandwidth
Shape Factor	$\pm$ 8%, RBW = 1MHz ; $\pm$ 5%, RBW < 1MHz	Nominal
	<4.5 : 1	Normal Bandwidth ratio: -60dB:-3dB

#### VIDEO BANDWIDTH (VBW) FILTER

Filter Bandwidth	1 Hz ~ 1 MHz in 1-3-10 sequence	-3dB bandwidth
------------------	---------------------------------	----------------

#### AMPLITUDE

##### AMPLITUDE RANGE

Measurement Range	100 kHz ~ 1 MHz 1 MHz ~ 10 MHz 10 MHz ~ 3 GHz	Displayed Average Noise Level(DANL) to 18 dBm DANL to 21 dBm DANL to 30 dBm
-------------------	---	---

##### ATTENUATOR

Input Attenuator Range	0 ~ 50 dB, in 1 dB steps	Auto or manual setup
------------------------	--------------------------	----------------------

##### MAXIMUM SAFE INPUT LEVEL

Average Total Power	$\leq$ +33 dBm	Input attenuator $\geq$ 10 dB
DC Voltage	$\pm$ 50 V	

##### 1 dB GAIN COMPRESSION

Total Power at 1st Mixer	> 0 dBm	Typical ; $F_c \geq$ 50 MHz; preamp. off
Total Power at the Preamp	> -22 dBm	Typical ; $F_c \geq$ 50 MHz; preamp. on
		Mixer power level (dBm) = input power (dBm) – attenuation (dB)

##### DISPLAYED AVERAGE NOISE LEVEL (DANL)

Preamp off	0 dB attenuation; RF Input is terminated with a 50 $\Omega$ load. RBW 10 Hz; VBW 10 Hz; span 500 Hz; reference level = - 60 dBm; trace average $\geq$ 40	
9 kHz~100 kHz	< -93 dBm	Nominal
100 kHz~1 MHz	< -90 dBm - 3 x (f/100 kHz) dB	Nominal
1 MHz~10 MHz	< -122 dBm	Nominal
2.7 ~ 3.25 GHz	< -116 dBm	Nominal
Preamp on	0 dB attenuation; RF Input is terminated with a 50 $\Omega$ load. RBW 10 Hz; VBW 10 Hz; span 500 Hz; reference level = - 60 dBm; trace average $\geq$ 40	
100 kHz~1 MHz	< -108 dBm - 3 x (f/100 kHz) dB	Nominal
1 MHz~10 MHz	< -142 dBm	Nominal
10 MHz~3.25 GHz	< -142 dBm + 3 x (f/1 GHz) dB	Nominal

##### LEVEL DISPLAY RANGE

Scales	Log, Linear	
Units	dBm, dBmV, dBuV, V, W	
Marker Level Readout	0.01 dB	Log scale
Level Display Modes	0.01 % of reference level	Linear scale
Number of Traces	Trace, Topographic, Spectrogram	Single/Split Windows
Detector	4	
Trace Functions	Positive-peak,negative-peak,sample,normal,RMS(not Video), Quasi-Peak(EMI),Average(EMI),Clear & Write,Max/Min Hold, View, Blank, Average	

##### ABSOLUTE AMPLITUDE ACCURACY

Absolute Point	Center=160 MHz ; RBW 10 kHz; VBW 1 kHz; span 100 kHz; log scale; 1 dB/div; peak detector; 23°C $\pm$ 1°C; Signal at Reference Level	
Preamp Off	$\pm$ 0.3 dB	Ref level 0 dBm; 10 dB RF attenuation
Preamp On	$\pm$ 0.4 dB	Ref level 0 dBm; -30 dB RF attenuation

##### FREQUENCY RESPONSE

Preamp Off	Attenuation : 10 dB; Reference: 160 MHz; 20 ~ 30°C	
100 kHz ~ 2.0 GHz	$\pm$ 0.5 dB	
2GHz ~ 3 GHz	$\pm$ 0.7 dB	
Preamp On	Attenuation: 0 dB; Reference: 160 MHz; 20 ~ 30°C	
1 MHz ~ 2 GHz	$\pm$ 0.6 dB	
2 GHz ~ 3 GHz	$\pm$ 0.8 dB	

##### ATTENUATION SWITCHING UNCERTAINTY

Attenuator Setting	0 ~ 50 dB in 1 dB step	
Uncertainty	$\pm$ 0.25 dB	Reference : 160 MHz, 10dB attenuation

##### RBW FILTER SWITCHING UNCERTAINTY

1 Hz ~ 1 MHz	$\pm$ 0.25 dB	Reference : 10 kHz RBW
--------------	---------------	------------------------

##### LEVEL MEASUREMENT UNCERTAINTY

Overall Amplitude Accuracy	$\pm$ 1.5 dB	20 ~ 30°C; frequency > 1 MHz; Signal input 0 ~ -50 dBm; Reference level 0 ~ -50 dBm; Input attenuation 10 dB; RBW 1 kHz; VBW 1 kHz; after cal; Preamp Off
	$\pm$ 0.5 dB	Typical

##### SPURIOUS RESPONSE

Second Harmonic Intercept	+35 dBm +60 dBm	Preamp off; signal input -30dBm; 0 dB attenuation Typical; 10 MHz < fc < 775 MHz Typical; 775 MHz $\leq$ fc < 1.625 GHz
Third-order Intercept	> 1dBm	Preamp off; signal input -30dBm; 0 dB attenuation 300 MHz ~ 3 GHz
Input Related Spurious Residual Response (Inherent)	< -60 dBc < -90 dBm	Input signal level -30 dBm, Att. Mode, Att = 0dB; 20 ~ 30°C Input terminated; 0 dB attenuation; Preamp off

## SPECIFICATIONS

SWEEP		
<b>SWEEP TIME</b>		
Range	204 $\mu$ s ~ 1000 s 50 $\mu$ s ~ 1000 s	Span > 0 Hz Span = 0 Hz; Min resolution = 10 $\mu$ s
Sweep Mode	Continuous; Single	
Trigger Source	Free run; Video; External	
Trigger Slope	Positive or negative edge	
<b>RF PREAMPLIFIER</b>		
Frequency Range	1 MHz ~ 3 GHz	
Gain	18 dB	Nominal (installed as standard)
<b>FRONT PANEL INPUT/OUTPUT</b>		
<b>RF INPUT</b>		
Connector Type	N-type female	
Impedance	50 $\Omega$	Nominal
VSWR	<1.6 :1	300 kHz ~ 3 GHz ; Input attenuator $\geq$ 10 dB
<b>POWER FOR OPTION</b>		
Connector Type	SMB male	
Voltage/Current	DC +7V/500 mA max	With short-circuit protection
<b>USB HOST</b>		
Connector Type	A plug	
Protocol	Version 2.0	Support Full/High/Low speed
<b>MICRO SD SOCKET</b>		
Protocol	SD 1.1	
Support Cards	Micro SD, Micro SDHC	Up to 32GB capacity
<b>REAR PANEL INPUT/OUTPUT</b>		
<b>REFERENCE OUTPUT</b>		
Connector Type	BNC female	
Output Frequency	10 MHz	Nominal
Output Amplitude	3.3V CMOS	
Output Impedance	50 $\Omega$	
<b>REFERENCE INPUT</b>		
Connector Type	BNC female	
Input Reference Frequency	10 MHz	
Input Amplitude	-5 dBm ~ +10 dBm	
Frequency Lock Range	Within $\pm$ 5 ppm of the input reference frequency	
<b>ALARM OUTPUT</b>		
Connector Type	BNC female	Open-collector
<b>TRIGGER INPUT/GATED SWEEP INPUT</b>		
Connector Type	BNC female	
Input Amplitude	3.3V CMOS	
Switch	Auto selection by function	
<b>LAN TCP/IP INTERFACE</b>		
Connector Type	RJ-45	
Base	10Base-T; 100Base-Tx; Auto-MDIX	
<b>USB DEVICE</b>		
Connector Type	B plug	
Protocol	Version 2.0	For remote control only; supports USB TMC Supports Full/High/Low speed
<b>IF OUTPUT</b>		
Connector Type	SMA female	
Impedance	50 $\Omega$	Nominal
IF Frequency	886 MHz	Nominal
Output Level	-25 dBm	10 dB attenuation; RF input : 0 dBm @ 1 GHz
<b>EARPHONE OUTPUT</b>		
Connector Type	3.5mm stereo jack, wired for mono operation	
<b>VIDEO OUTPUT</b>		
Connector Type	DVI-I (integrated analog and digital), Single Link. Compatible with VGA or HDMI standard through adapter	
<b>RS-232C INTERFACE</b>		
Connector Type	D-sub 9-pin female	Tx , Rx , RTS , CTS
<b>GPIB INTERFACE (OPTIONAL)</b>		
Connector Type	IEEE-488 bus connector	
<b>AC POWER INPUT</b>		
Power Source	AC 100 V ~ 240 V, 50/60 Hz	Auto range selection
<b>BATTERY PACK (OPTIONAL)</b>		
Battery Pack	6 cells, Li-Ion rechargeable, 3S2P	
Voltage	DC 10.8 V	With UN38.3 Certification
Capacity	5200 mAh/56Wh	
<b>GENERAL</b>		
Internal Data Storage	16 MB nominal	
Power Consumption	< 65 W	
Warm-up Time	< 30 minutes	
Temperature Range	+5 $^{\circ}$ C ~ + 45 $^{\circ}$ C -20 $^{\circ}$ C ~ + 70 $^{\circ}$ C	Operating Storage
Dimensions & Weight	350(W) x 210(H) x 100(D) mm, Approx. 4.5kg 13.8(W) x 8.3(H) x 3.9(D) inch, Approx. 9.9lb	Inc. all options (Basic + TG + GPIB + Battery)
<b>TRACKING GENERATOR (OPTIONAL)</b>		
Frequency Range	100 kHz ~ 3 GHz	
Output Power	-50 dBm ~ 0 dBm in 0.5 dB steps	
Connector Type	N-type female	50 $\Omega$ Nominal
Output VSWR	< 1.6 : 1	300 kHz ~ 3 GHz, source attenuation $\geq$ 12 dB

Note : The specifications apply when the GSP-9300B is powered on for at least 30 minutes to warm-up to a temperature of 20  $^{\circ}$ C to 30  $^{\circ}$ C, unless specified otherwise.

Specifications subject to change without notice. GSP-9300BGD1DH

### ORDERING INFORMATION

**GSP-9300B** 3 GHz Spectrum Analyzer

**EMC Pretest Solution :** GKT-008 EMI Near Field Probe Set  
GLN-5040A Line Impedance Stabilization Network  
GIT-5060 Isolation transformer  
GPL-5010 Transient Limiter

#### ACCESSORIES :

Power Cord, Certificate of Calibration, CD-ROM (with Quick Start Guide, User Manual, Programming Manual, SpectrumShot Software, SpectrumShot Guide & IVI Driver)

### OPTIONS

**Opt.01** Tracking Generator **Opt.03** GPIB Interface  
**Opt.02** Battery Pack

### OPTIONAL ACCESSORIES

**GSC-009** Soft Carrying Case  
**GRA-415** Rack Adapter Panel

### FREE DOWNLOAD

SpectrumShot PC Software for Windows System (available on GW Instek website)  
IVI Driver Supports LabVIEW/LabWindows/CVI Programming (available on NI website)