

**GW INSTEK**  
Simply Reliable

**GDM-500 Series**  
Hand-Held Digital Multimeter



**FEATURES**

**GDM-541 FEATURES**

- \* 22000 Counts Auto/Manual Ranging
- \* 46 Segments Analogue Bar
- \* ACV Measurement up to 1000V
- \* AC+DC Voltage Measurement
- \* Current Measurement up to 20A
- \* Transistor (hFE) Measurement
- \* Audible/Visual Alarm when Overload
- \* True RMS/USB Interface

**GDM-533 FEATURES**

- \* 6000 Counts Auto/Manual Ranging
- \* 31 Segments Analogue Bar
- \* LoZ ACV Measurement
- \* ACV Measurement up to 1000V
- \* Current Measurement up to 20A
- \* Temperature Measurement
- \* Audible/Visual Alarm when Overload
- \* True RMS/USB Interface

**GDM-532 FEATURES**

- \* 9999 Counts Auto/Manual Ranging
- \* Display Backlight/Auto Power Off
- \* Continuity Beeper/Diode Test
- \* Temperature Measurement
- \* Non-Contact Voltage (NCV) Detection
- \* Data Hold and Relative Mode

**GDM-531 FEATURES**

- \* 6000 Counts Manual Ranging
- \* Display Backlight/Auto Power Off
- \* Capacitance Measurement
- \* Non-Contact Voltage (NCV) Detection
- \* Data Hold
- \* Audible/Visual Alarm when Overload

The GDM-500 Series Hand Held DMM are a compact, high precision, battery operated multimeter series designed to meet of service engineers. The GDM-500 Series design is driven by mobile-oriented features: automatic power off to preserve battery life, a large backlight display for crisp viewing, a rotary selector and push buttons to ease operation, and then NCV (Non-Contact Voltage) function for outdoor use.

The basic functions match the depth of bench-top multimeters: fuse-protected current input, true RMS for accurate AC measurements, Audible/Visual Alarm when Overload, Auto ranging, Duty cycle and Relative mode. The compact, reliable and economical devices are ideal for any engineer.

**SELECTION GUIDE**

MODEL	GDM-541	GDM-533	GDM-532	GDM-531
Max. Display	22000	6000	9999	6000
Auto Ranging	✓	✓	✓	
Analog Bar	✓	✓	✓	
True RMS	✓	✓	✓	
Display Backlight	✓	✓	✓	✓
Auto Power off	✓	✓	✓	✓
Curr. Range Protection	PTS & Fuse	PTS & Fuse	Fuse	Fuse
DC Voltage	1000V	1000V	999.9V	600V
AC Voltage	1000V	1000V	999.9V	600V
DC Current	20A	20A	9.99A	10A
AC Current	20A	20A	9.99A	
Resistance	220MΩ	60MΩ	99.99MΩ	60MΩ
Capacitance	220mF	60mF	9.999mF	9.999mF
Frequency	220MHz	10MHz	9.9MHz	
Diode	✓	✓	✓	✓
Continuity	✓	✓	✓	✓
Temperature		✓	✓	✓
Duty Cycle (%)	✓		✓	
Transistor (hFE)	✓	✓	✓	
NCV Function	✓	✓	✓	✓
REL	✓	✓	✓	
Data Hold	✓	✓	✓	✓
Peak Hold	✓	✓	✓	
MAX MIN	✓	✓	✓	
LoZ ACV		✓		
LPF ACV	✓			
Audible / Visual Alarm	✓	✓	✓	✓
AC+DC Measurement	✓			
Interface	USB	USB		
Safety Rating	CAT III 1000V CAT IV 600V	CAT III 1000V CAT IV 600V	CAT II 1000V CAT III 600V	CAT III 600V

SPECIFICATIONS		
<b>DC VOLTAGE</b>	<b>Range</b>	220.00mV, 2.2000V, 22.000V, 220.00V, 1000V(GDM-541) 60.00mV, 600.0mV, 6.000V, 60.00V, 600.0V, 1000V(GDM-533) 9.999mV, 99.99mV, 999.9mV, 9.999V, 99.99V, 999.9V(GDM-532) 600.0mV, 6000mV, 60.00V, 600.0V(GDM-531)
	<b>Best Accuracy</b>	±(0.05%rdg + 5 digits) for GDM-541; ±(0.5%rdg + 3 digits) for GDM-533 ±(0.5%rdg + 3 digits) for GDM-532; ±(0.7%rdg + 3 digit) for GDM-531
	<b>Input Impedance</b>	10 MΩ (At mV range : 1GΩ for GDM-541/533; 3GΩ for GDM-532)
<b>AC VOLTAGE</b>	<b>Range</b>	220.00mV, 2.2000V, 22.000V, 220.00V, 1000.0V(GDM-541) 60.00mV, 600.0mV, 6.000V, 60.00V, 600.0V, 1000V(GDM-533) 9.999mV, 99.99mV, 999.9mV, 9.999V, 99.99V, 999.9V(GDM-532) 600.0V(GDM-531)
	<b>Best Accuracy</b>	±(0.8%rdg + 10 digits) for GDM-541; ±(1.0%rdg + 3 digits) for GDM-533 ±(0.8%rdg + 3 digits) for GDM-532; ±(1.2%rdg + 3 digits) for GDM-531
	<b>Frequency Response</b>	40Hz-10kHz for GDM-541; 40Hz-1kHz for GDM-533 45Hz-400Hz for GDM-532; 40Hz-400Hz for GDM-531
	<b>Input Impedance</b>	10 MΩ
<b>DC CURRENT</b>	<b>Range</b>	220.00μA, 2200.0μA, 22.000mA, 220.00mA, 20.000A(GDM-541) 600.0μA, 6000μA, 60.00mA, 600.0mA, 6.000A, 20.00A(GDM-533) 999.9μA, 999.9mA, 9.999A(GDM-532) 600.0μA, 60.00mA, 600.0mA, 10.00A(GDM-531)
	<b>Best Accuracy</b>	±(0.5%rdg + 10 digits) for GDM-541; ±(1.0%rdg + 2 digits) for GDM-533 ±(0.8%rdg + 3 digits) for GDM-532; ±(1.0%rdg + 3 digits) for GDM-531
<b>AC CURRENT</b>	<b>Range</b>	220.00μA, 2200.0μA, 22.000mA, 220.00mA, 20.000A(GDM-541) 600.0μA, 6000μA, 60.00mA, 600.0mA, 6.000A, 20.00A(GDM-533) 999.9μA, 999.9mA, 9.999A(GDM-532)
	<b>Best Accuracy</b>	±(0.8%rdg + 10 digits) for GDM-541; ±(1.2%rdg + 5 digits) for GDM-533 ±(1.0%rdg + 3 digits) for GDM-532
<b>RESISTANCE</b>	<b>Range</b>	220.00Ω, 2.2000kΩ, 22.000kΩ, 220.00kΩ, 2.2000MΩ, 22.000MΩ, 220.00MΩ(GDM-541) 600.0Ω, 6.000kΩ, 60.00kΩ, 600.0kΩ, 6.000MΩ, 60.00MΩ(GDM-533) 999.9Ω, 9.999kΩ, 99.99kΩ, 999.9kΩ, 9.999MΩ, 99.99MΩ(GDM-532) 600.0Ω, 6000Ω, 60.00kΩ, 600.0kΩ, 60.00MΩ(GDM-531)
	<b>Best Accuracy</b>	±(0.5%rdg + 10 digits) for GDM-541; ±(1.0%rdg + 2 digit) for GDM-533 ±(0.8%rdg + 2 digits) for GDM-532; ±(0.8%rdg + 2 digits) for GDM-531
<b>CONTINUITY BEEPER</b>		Buzzer sounds if conductance less than 50Ω for GDM-541/533 Buzzer sounds if conductance less than 30Ω for GDM-532 Buzzer sounds if conductance less than 10Ω for GDM-531
<b>DIODE TEST</b>	<b>Open Circuit Voltage</b>	GDM-541/533 : 3V (Approx.); GDM-532 : 3.3V (Approx.); GDM-531 : 2.1V (Approx.)
<b>CAPACITANCE</b>	<b>Range</b>	22.000nF, 220.00nF, 2.2000μF, 22.000μF, 220.00μF, 2.2000mF, 22.000mF, 220.00mF(GDM-461) 60.00nF, 600.0nF, 6.000μF, 60.00μF, 600.0μF, 6.000mF, 60.00mF(GDM-533)
	<b>Best Accuracy</b>	9.999nF, 99.99nF, 999.9nF, 9.999μF, 99.99μF, 999.9μF, 9.999mF(GDM-532/531) ±(3.0%rdg + 5 digits) for GDM-541/533; ±(4.0%rdg + 5 digits) for GDM-532/531
<b>FREQUENCY</b>	<b>Range</b>	10Hz ~ 220MHz(GDM-541); 10Hz ~ 10MHz(GDM-533); 99.99Hz ~ 9.999MHz(GDM-532)
	<b>Best Accuracy</b>	±(0.01%rdg + 5 digits) for GDM-541; ±(0.1%rdg + 4 digits) for GDM-533 ±(0.1%rdg + 5 digits) for GDM-532
	<b>Input Amplitude</b>	≤ 20Vrms
<b>TEMPERATURE</b>	<b>Range</b>	-40°C ~ 1000°C / -40°F ~ 1832°F
	<b>Best Accuracy</b>	±(1.0%rdg + 3 °C) for GDM-533; ±(1.0%rdg + 5 °C) for GDM-532 ±(1.0%rdg + 4 °F) for GDM-533; ±(1.5%rdg + 5 °F) for GDM-532
<b>SPECIAL FUNCTION</b>		Auto Ranging(GDM-541/533/532); True RMS(GDM-541/533/532); Analog Bar(GDM-541/533); USB(GDM-541/533); Display Backlight(GDM-541/533/532/531); NCV Function (GDM-541/533/532/531); Audible/Visual Alarm(GDM-541/533/532/531); AC+DC Voltage (GDM-541); LPF ACV(GDM-541); hFE Test(GDM-541); LoZ ACV(GDM-533)
<b>LCD DISPLAY</b>		22000 counts (GDM-541), 6000 counts (GDM-533/531), 9999 counts (GDM-532)
<b>POWER SOURCE</b>		1.5V AAA x 4 (GDM-541/533); 1.5V AAA x 3 (GDM-532); 1.5V AAA x 2 (GDM-531)
<b>DIMENSIONS &amp; WEIGHT</b>		89(W) x 186(H) x 49(D) mm, Approx. 400g (GDM-541/533) 81(W) x 169(H) x 46(D) mm, Approx. 400g (GDM-532) 76.5(W) x 155(H) x 49(D) mm, Approx. 255g (GDM-531)

GDM-500\_E\_D1DH\_202205

ORDERING INFORMATION	
<b>GDM-541</b>	22000 Counts Hand-Held DMM with True RMS Measurement and USB Interface
<b>GDM-533</b>	6000 Counts Hand-Held DMM with True RMS Measurement and USB Interface
<b>GDM-532</b>	9999 Counts Hand-Held DMM with True RMS Measurement
<b>GDM-531</b>	6000 Counts Hand-Held DMM

ACCESSORIES	
User manual, Test leads, Battery, USB cable & Adapter socket (GDM-541/533 only), K-type thermocouple (GDM-533/532 only)	
FREE DOWNLOAD	
<b>GDM-541 PC Software</b>	Remote Software
<b>GDM-533 PC Software</b>	Remote Software