

# U1270 Series Handheld Digital Multimeter



## Be Ready for Harsh Environments and Sub-zero Temperature

The U1273AX, the latest addition to the U1270 Series is capable of operating down to -40 °C in temperature. Even in extremely cold conditions, the U1273AX handheld DMM delivers immediate and accurate results — no warm-up time required.

All models are ergonomically built providing useful functions such as ZLOW, which eliminates stray voltages, and Smart Ohm that minimizes false readings from residual voltage induced by leakage current. All of this is designed into a case that fulfills the needs of today's industrial handheld users.

## Features

- OLED display with 2000:1 contrast ratio and 160 degrees viewing angle <sup>3,4</sup>
- 30,000-count resolution
- Measure up to 1000 V AC and DC
- Measure up to 10 A (20 A for 30 s)
- Resistance, diode test, temperature, capacitance
- Low Impedance mode <sup>2,3,4</sup> and Low Pass Filter
- Peak detection of up to 250 µs
- Continuity test with beeper and backlight <sup>1,2</sup>
- Seven readings/s measurement rate for voltage and current
- Smooth function for accurately stable readings
- Up to 10,000 points internal memory for data logging
- PC connectivity with optional U1173B IR-USB cable
- IP 54 certified – water and dust resistant
- CAT III 1000 V, CAT IV 600 V safety rating
- Up to 3000m operating altitude
- -40 to 55 °C operating temperature <sup>4</sup>

1. U1271A
2. U1272A
3. U1273A
4. U1273AX



Ihr Ansprechpartner /  
Your Partner:

dataTec AG  
E-Mail: [info@datatec.eu](mailto:info@datatec.eu)  
>>> [www.datatec.eu](http://www.datatec.eu)

 **KEYSIGHT**  
Authorized Premium  
Distributor

# Operational Down to -40 °C Temperature

The U1273AX OLED handheld digital multimeter, the latest addition to U1270 Series, is capable of operating in winter weather down to -40 °C temperature. Even in frigid conditions, the U1273AX enables you to achieve immediate and accurate results without the need to warm up in advance.



## OLED for More Display Clarity

Designed with OLED display, you can experience crystal-clear measurement readings with its outstanding 2000:1 contrast ratio. The display also allows wider viewing angles up to 160 degrees ensuring you get the right readings at the first glance even in poorly lit environments.



# Key Functions

## Water and dust resistance (IP54)

The series' tightly sealed design helps protect against water, dust and damage. Each handheld DMM is certified with IP 54 ratings so that you can carry out tests and measurements with confidence, even in harsh working conditions.

## Operational up to 3000 meters altitude

For high altitude applications such as wind farm maintenance, you can measure with confidence using the U1270 Series, capable of measuring up to 3000 meters above sea level.

## High measurement rate at seven readings per second for Voltage and Current

You can detect even the slightest change in your sensitive signals (Voltage and Current) with its high measurement rate capability. By clicking the resettable smooth function button, you may customize the readings' sensitivity suitable for various tests.

## Visual alert for continuity test (for U1271A and U1272A only)

Continuity detection in noisy and dark environments is made easy with U1270 Series' loud beeper and flashing backlight that indicates continuity and thus improves safety.

## Up to 10,000 recording points for manual, auto and event logging

Record measurements on-the-go and transfer data to PC conveniently with the huge internal memory of up to 10,000 recording points. The GUI Data Logging software and optional U1173A IR-USB cable are required to transfer data or perform real time data logging on a PC.

## Built-in Low Pass Filter

The U1270 Series offers a 440 Hz LPF or Low Pass Filter to provide accurate output measurements. This function eliminates high-frequency noise and harmonics, ensuring motor filter efficiency.

## Low impedance mode

Stray voltages are usually found in non-energized electrical wiring adjacent to powered wires due to capacitive or inductive coupling between these wires. The low impedance mode serves to eliminate false readings by dissipating these stray voltages thus improves safety and measurement efficiency during voltage measurement.

## Peak detect at 250 $\mu$ s

The peak detect function allows you to capture the engine or motor startup transient as fast as 250  $\mu$ s.

# Front and Back Panel Description





# Choose Among These Four Models

Basic features	U1271A	U1272A	U1273A	U1273AX
Display resolution	30,000 counts	30,000 counts	30,000 counts	30,000 counts
Display	LCD	LCD	OLED	OLED
Backlight	Yes	Yes	N/A	N/A
True RMS	AC	AC + DC	AC + DC	AC + DC
<b>Measurements</b>				
Voltage	Up to 1000 V AC, DC	Up to 1000 V AC, DC	Up to 1000 V AC, DC	Up to 1000 V AC, DC
Basic dcV accuracy	0.05% + 2 counts	0.05% + 2 counts	0.05% + 2 counts	0.05% + 2 counts
Current	Up to 10 A (20 A for 30 s)	Up to 10 A (20 A for 30 s)	Up to 10 A (20 A for 30 s)	Up to 10 A (20 A for 30 s)
Resistance	Up to 100 MΩ	Up to 300 MΩ	Up to 300 MΩ	Up to 300 MΩ
Other measurements	Frequency, capacitance, temperature, continuity, diode test	Frequency, capacitance, temperature, continuity, diode test	Frequency, capacitance, temperature, continuity, diode test	Frequency, capacitance, temperature, continuity, diode test
AC bandwidth	20 kHz	100 kHz	100 kHz	100 kHz
Low pass filter	Yes	Yes	Yes	Yes
Low impedance mode	—	Yes	Yes	Yes
Smart Ohm	—	Yes	Yes	Yes
<b>Safety and regulatory</b>				
Over-voltage safety protection	CAT III 1000 V, CAT IV 600 V	CAT III 1000 V, CAT IV 600 V	CAT III 1000 V, CAT IV 600 V	CAT III 1000 V, CAT IV 600 V
<b>General specifications</b>				
Logging memory	200 points	10,000 points	10,000 points	10,000 points
Connectivity	Optional IR-USB	Optional IR-USB	Optional IR-USB	Optional IR-USB
Operating temperature	-20 to 55 °C	-20 to 55 °C	-20 to 55 °C	-40 to 55 °C
Altitude	3000 meters	3000 meters	3000 meters	3000 meters
Water and dust ingress protection	IP 54	IP 54	IP 54	IP 54
Battery life	Up to 300 hours 4X AAA Alkaline	Up to 300 hours 4X AAA Alkaline	Up to 60 hours 4X AAA Alkaline	Up to 100 hours 4X AAA Lithium
Display	U1271A and U1272A: Liquid crystal display (LCD) (with maximum reading of 33,000 counts) U1273A/U1273AX: Organic LED (OLED) display (with maximum reading of 33,000 counts) (Note: OLED is made of organic materials and it has its lifespan.)			
Power consumption	U1271A/U1272A: 460 mVA maximum (with backlight enabled) U1273A/U1273AX: 180 mVA maximum (with maximum brightness)			
Battery type	4 × 1.5 V Alkaline battery (ANSI/NEDA 24A or IEC LR03), or 4 × 1.5 V Zinc Chloride battery (ANSI/NEDA 24D or IEC R03) 4 × 1.5 V Lithium battery (ANSI/NEDA 24LF or IEC FR03)			
Battery life	U1271A and U1272A: 300 hours typical (based on new Alkaline batteries for DC voltage measurement) U1273A/U1273AX: Based on new Alkaline batteries for DC voltage measurement: 30/45/60 hours typical at High/Medium/Low brightness, respectively Based on new Lithium batteries for DC voltage measurement: 50/100 hours typical at High/Low brightness, respectively Low battery indicator will flash when the battery voltage drops: For non-rechargeable batteries: 4.4 V (approximately) For rechargeable batteries: 4.5 V (approximately)			
Fuse	10 × 35 mm 440 mA/1000 V 30 kA fast-acting fuse 10 × 38 mm 11 A/1000 V 30 kA fast-acting fuse			
Input impedance at off mode	1.67 kΩ (protected by positive temperature coefficient resistor) (U1272A, U1273A and U1273AX only)			
Operating environment	Operating temperature: U1271A/ U1272A/U1273A: -20 to 55 °C, 0% to 80% RH U1273AX: -40 to 55 °C, 0% to 80% RH (using Lithium batteries) Full accuracy up to 80% RH for temperatures up to 30 °C, decreasing linearly to 50% RH at 55 °C Altitude up to 3000 meters Pollution degree II			

General specifications	
Storage compliance	-40 to 70 °C, 0 to 80% RH
Safety & EMC compliance	<p>Refer to Declaration of Conformity for the latest revisions of regulatory compliance at: <a href="http://www.keysight.com/go/conformity">www.keysight.com/go/conformity</a></p> <p>Commercial limits compliance with EN61326-1</p> <p>Influence of radiated immunity; in RF electromagnetic fields of 3 V/m</p> <p>DC voltage measurement typical accuracy</p> <p>All ranges; <math>\pm 0.03\%</math> of range</p> <p>DC current measurement typical accuracy</p> <p>300 <math>\mu</math>A, 3000 <math>\mu</math>A, 30 mA, 300 mA &amp; 3 A range; <math>\pm 0.22\%</math> of range</p> <p>10 A range; <math>\pm 0.66\%</math> of range</p> <p>Note:</p> <ul style="list-style-type: none"> <li>The measurement accuracy is applied only when DC Low Pass Filter (LPF) is ON (factory default).</li> <li>The use of LPF is recommended to improve the accuracy of measurements in the presence of RF fields.</li> <li>If used in close proximity to an RF transmitter or when subjected to continuously present electromagnetic phenomena, some recoverable degradation of performance may occur.</li> </ul>
Measurement category	CAT III 1000 V/CAT IV 600 V
Ingress protection rating	IP-54
Temperature coefficient	<p>U1271A/U1272A/U1273A: <math>0.05 \times (\text{specified accuracy})/^{\circ}\text{C}</math> (from <math>-20</math> to <math>18^{\circ}\text{C}</math>, or <math>28</math> to <math>55^{\circ}\text{C}</math>)</p> <p>U1273AX: <math>0.05 \times (\text{specified accuracy})/^{\circ}\text{C}</math> (from <math>-40</math> to <math>18^{\circ}\text{C}</math>, or <math>28</math> to <math>55^{\circ}\text{C}</math>)</p>
Common Mode Rejection Ratio (CMRR)	$> 120$ dB at DC, 50/60 Hz $\pm 0.1\%$ (1 k $\Omega$ unbalanced)
Normal Mode Rejection Ratio (NMRR)	$> 60$ dB at 50/60 Hz $\pm 0.1\%$
Dimensions (W x H x D)	92 x 207 x 59 mm
Weight	<p>U1271A: 518 grams (with batteries)</p> <p>U1272A: 520 grams (with batteries)</p> <p>U1273A: 500 grams (with batteries)</p> <p>U1273AX: 500 grams (with batteries)</p>
Calibration cycle	One year

## Specification assumptions

- Accuracy is given as  $\pm$  (% of reading + counts of least significant digit) at  $23^{\circ}\text{C} \pm 5^{\circ}\text{C}$ , with relative humidity less than 80% RH.
- AC V and AC  $\mu$ A/mA/A specifications are AC coupled, true RMS and are valid from 5% of range to 100% of range.
- Crest factor  $\leq 3$  at full-scale and decrease reciprocally for overrange as  $3 \times \text{Full Scale} / \text{Input}$ ; except for the 1000 V range, where this range has a crest factor  $\leq 1.5$  at full scale and decrease reciprocally for overrange as
- $1.5 \times \text{Full Scale} / \text{Input}$ .
- For non-sinusoidal waveforms, add (2% of reading + 2% of full scale) typical.
- After ZLOW voltage measurements, wait at least 20 minutes for thermal impact to cool before proceeding with any other measurement.

# Electrical Specifications

## DC specifications for U1271A, U1272A, U1273A and U1273AX

Function	Range	Resolution	Accuracy $\pm$ (% of reading + counts of least significant digit)			Test current / burden voltage
			U1271A	U1272A	U1273A / U1273AX	
Voltage <sup>1</sup>	30 mV	0.001 mV	—	0.05 + 20	0.05 + 20	—
	300 mV	0.01 mV	0.05 + 5	0.05 + 5	0.05 + 5	—
	3 V	0.0001 V	0.05 + 5	0.05 + 5	0.05 + 5	—
	30 V	0.001 V	0.05 + 2	0.05 + 2	0.05 + 2	—
	300 V	0.01 V	0.05 + 2	0.05 + 2	0.05 + 2	—
	1000 V	0.1 V	0.05 + 2	0.05 + 2	0.05 + 2	—
	ZLOW (low impedance) enabled, applicable for 1000 V range and resolution only	0.1 V	—	1 + 20	1 + 20	—
Resistance <sup>2</sup>	30 $\Omega$	0.001 $\Omega$	—	0.2 + 10	0.2 + 10	0.65 mA
	300 $\Omega$	0.01 $\Omega$	0.2 + 5	0.2 + 5	0.2 + 5	0.65 mA
	3 k $\Omega$	0.0001 k $\Omega$	0.2 + 5	0.2 + 5	0.2 + 5	65 $\mu$ A
	30 k $\Omega$	0.001 k $\Omega$	0.2 + 5	0.2 + 5	0.2 + 5	6.5 $\mu$ A
	300 k $\Omega$	0.01 k $\Omega$	0.2 + 5	0.2 + 5	0.2 + 5	0.65 $\mu$ A
	3 M $\Omega$	0.0001 M $\Omega$	0.6 + 5	0.6 + 5	0.6 + 5	93 nA/10 M $\Omega$
	30 M $\Omega$	0.001 M $\Omega$	1.2 + 5	1.2 + 5	1.2 + 5	93 nA/10 M $\Omega$
	100 M $\Omega$	0.01 M $\Omega$	2.0 + 10	—	—	93 nA/10 M $\Omega$
	300 M $\Omega$	0.01 M $\Omega$	—	2.0 + 10 @ < 100 M $\Omega$ 8.0 + 10 @ > 100 M $\Omega$	2.0 + 10 @ < 100 M $\Omega$ 8.0 + 10 @ > 100 M $\Omega$	93 nA/10 M $\Omega$
	300 nS	0.01 nS	1 + 10	1 + 10	1 + 10	93 nA/10 M $\Omega$
Current <sup>3</sup>	300 $\mu$ A	0.01 $\mu$ A	0.2 + 5	0.2 + 5	0.2 + 5	< 0.04 V/100 $\Omega$
	3000 $\mu$ A	0.1 $\mu$ A	0.2 + 5	0.2 + 5	0.2 + 5	< 0.4 V/100 $\Omega$
	30 mA	0.001 mA	0.2 + 5	0.2 + 5	0.2 + 5	< 0.08 V/1 $\Omega$
	300 mA	0.01 mA	0.2 + 5	0.2 + 5	0.2 + 5	< 1.00 V/1 $\Omega$
	3 A4	0.0001 A	0.3 + 10	0.3 + 10	0.3 + 10	< 0.1 V/0.01 $\Omega$
	10 A4	0.001 A	0.3 + 10	0.3 + 10	0.3 + 10	< 0.3 V/0.01 $\Omega$
Diode test <sup>5</sup>	3 V	0.0001 V	0.5 + 5	0.5 + 5	0.5 + 5	Approximately 1 to 2 mA
	Auto	0.0001 V	—	0.5 + 5	0.5 + 5	Approximately 1 to 2 mA

## Notes for DC specifications (previous page)

1. Notes for voltage specifications:
  - The accuracy of the 30 to 300 mV range is specified after the Null function is used to subtract the thermal effect (by shorting the test leads).
  - ZLow impedance: 2 k $\Omega$ m (nominal). For ZLow measurements, autoranging is disabled and the multimeter's range is set to 1000 volts in the manual ranging mode.
2. Notes for resistance specifications:
  - Overload protection: 1000 Vrms for short circuits with < 0.3 A current.
  - Maximum open voltage is < +3.3 V.
  - Built-in buzzer beeps when the resistance measured is less than 25  $\Omega$   $\pm$  10  $\Omega$ . The multimeter can capture intermittent measurements longer than 1 ms.
  - U1272A/73A/73AX only: The accuracy of the 30  $\Omega$  to 3 k $\Omega$  range is specified after the Null function is used to subtract the test lead resistance and thermal effect (by shorting the test leads).
  - U1271A only: The accuracy of the 300  $\Omega$  to 3 k $\Omega$  range is specified after the Null function is used to subtract the test lead resistance and thermal effect (by shorting the test leads).
  - U1273AX only: The accuracy for all resistance ranges is specified after the Null function is used when measuring at temperatures below -20  $^{\circ}$ C. The Null function is used to subtract the test lead resistance and thermal effect (by shorting the test leads).
  - For the ranges of 30 M $\Omega$  and 100 M $\Omega$ , the RH is specified for < 60%.
  - The accuracy for ranges < 50 nS is specified after the Null function is used on an open test lead.
  - The temperature coefficient of the 100 M $\Omega$  and 300 M $\Omega$  range is 0.1  $\times$  (specified accuracy)/ $^{\circ}$ C (from -40 to 18  $^{\circ}$ C or 28 to 55  $^{\circ}$ C).
3. Notes for current specifications:
  - Overload protection for 300  $\mu$ A to 300 mA range: 0.44 A/1000 V; 10  $\times$  35 mm 30 kA fast-acting fuse.
  - Overload protection for 3 A to 10 A range: 11 A/1000 V; 10  $\times$  38 mm 30 kA fast-acting fuse.
  - Specification for 300 mA range: 440 mA continuous.
  - Specification for 10 A range: 10 A continuous. Add 0.3% to the specified accuracy when measuring signals > 10 to 20 A for 30 seconds maximum. After measuring currents > 10 A, cool down the multimeter for twice the duration of the measured time before proceeding with low current measurements.
4. Specification applies with settling time of (1.2 $\times$ Current $^2$ ) seconds. For example, DCI: 3 A will require 11 s of settling time.
5. Notes for diode specifications:
  - Overload protection: 1000 Vrms for short circuits with < 0.3 A current.
  - Built-in buzzer beeps continuously when the voltage measured is less than 50 mV and beeps once for forward-biased diode or semiconductor junctions measured between 0.3 V and 0.8 V (0.3 V  $\leq$  reading  $\leq$  0.8 V).
  - Open voltage for diode: < +3.3 V DC.
  - Open voltage for Auto diode: < +2.5 V DC and > -1.0 V DC.



## AC specifications for U1271A

Accuracy  $\pm$  (% of reading + counts of least significant digit)

Function	Range	Resolution	45 Hz to 65 Hz	30 Hz to 1 kHz	1 kHz to 5 kHz	5 kHz to 20 kHz
True RMS AC voltage <sup>1</sup>	300 mV	0.01 mV	0.7 + 20	1.0 + 25	2.0 + 25	2.0 + 40
	3 V	0.0001 V	0.7 + 20	1.0 + 25	2.0 + 25	2.0 + 40
	30 V	0.001 V	0.7 + 20	1.0 + 25	2.0 + 25	2.0 + 40
	300 V	0.01 V	0.7 + 20	1.0 + 25	2.0 + 25	—
	1000 V	0.1 V	0.7 + 20	1.0 + 25	—	—
	LPF (low pass filter) enabled, applicable for all voltage ranges and resolution		0.7 + 20	1.0 + 25@<200 Hz 5.0 + 25@<440 Hz	—	—

Accuracy  $\pm$  (% of reading + counts of least significant digit)

Function	Range	Resolution	45 Hz to 2 kHz	Burden voltage/Shunt
True RMS AC current <sup>2</sup>	300 $\mu$ A	0.01 $\mu$ A	0.9 + 25	< 0.04 V/100 $\Omega$
	3000 $\mu$ A	0.1 $\mu$ A	0.9 + 25	< 0.4 V/100 $\Omega$
	30 mA	0.001 mA	0.9 + 25	< 0.08 V/1 $\Omega$
	300 mA	0.01 mA	0.9 + 25	< 1.00 V/1 $\Omega$
	3 A	0.0001 A	1.0 + 25	< 0.1 V/0.01 $\Omega$
	10 A	0.001 A	1.0 + 25	< 0.3 V/0.01 $\Omega$

1. Notes for voltage specifications:

- Overload protection: 1000 Vrms. For millivolt measurements, 1000 Vrms for short circuits with < 0.3 A current.
- Input impedance: 10 M $\Omega$  (nominal) in parallel with < 100 pF.

2. Notes for current specifications:

- Overload protection for 300  $\mu$ A to 300 mA range: 0.44 A/1000 V; 10  $\times$  35 mm 30 kA fast-acting fuse.
- Overload protection for 3 A to 10 A range: 11 A/1000 V; 10  $\times$  38 mm 30 kA fast-acting fuse.
- Specification for 300 mA range: 440 mA continuous.
- Specification for 10 A range: 10 A continuous. Add 0.3% to the specified accuracy when measuring signals > 10 to 20 A for 30 seconds maximum. After measuring currents > 10 A, cool down the multimeter for twice the duration of the measured time before proceeding with low current measurements.

## AC specifications for U1272A/U1273A and U1273AX

Accuracy  $\pm$  (% of reading + counts of least significant digit)

Function	Range	Resolution	45 Hz to 65 Hz	20 Hz to 1 kHz	1 kHz to 5 kHz	5 kHz to 20 kHz	20 kHz to 100 kHz
True RMS AC voltage <sup>1</sup>	30 mV	0.001 mV	0.6 + 20	0.7 + 25	1.0 + 25	1.0 + 40	3.5 + 40
	300 mV	0.01 mV	0.6 + 20	0.7 + 25	1.0 + 25	1.0 + 40	3.5 + 40
	3 V	0.0001 V	0.6 + 20	1.0 + 25	1.5 + 25	2.0 + 40	3.5 + 40
	30 V	0.001 V	0.6 + 20	1.0 + 25	1.5 + 25	2.0 + 40	3.5 + 40
	300 V	0.01 V	0.6 + 20	1.0 + 25	1.5 + 25	2.0 + 40	—
	1000 V	0.1 V	0.6 + 20	1.0 + 25	1.5 + 25	—	—
	LPF (low pass filter) enabled, applicable for all voltage ranges and resolution		0.6 + 20	1.0 + 25 @ < 200 Hz 5.0 + 25 @ < 440 Hz	—	—	—
	ZLOW 1000 V		2.0 + 40	2 + 40 @ < 440 Hz	—	—	—

Function	Range	Resolution	Accuracy ± (% of reading + counts of least significant digit)		Burden voltage/Shunt
			45 Hz to 65 Hz	20 Hz to 2 kHz	
True RMS AC current <sup>2</sup>	300 µA	0.01 µA	0.6 + 25	0.9 + 25	< 0.04 V / 100 Ω
	3000 µA	0.1 µA	0.6 + 25	0.9 + 25	< 0.4 V / 100 Ω
	30 mA	0.001 mA	0.6 + 25	0.9 + 25	< 0.08 V / 1 Ω
	300 mA	0.01 mA	0.6 + 25	0.9 + 25	< 1.00 V / 1 Ω
	3 A	0.0001 A	0.8 + 25	1.0 + 25	< 0.1 V / 0.01 Ω
	10 A	0.001 A	0.8 + 25	1.0 + 25	< 0.3 V / 0.01 Ω

1. Notes for voltage specifications:

- Overload protection: 1000 Vrms. For millivolt measurements, 1000 Vrms for short circuits with < 0.3 A current.
- Input impedance: 10 MΩ (nominal) in parallel with < 100 pF.
- ZLOW impedance: 2 kΩ (nominal).
- The input signal is lower than the product of 20,000,000 V×Hz.
- For 20 to 100 kHz accuracy: Three counts of the LSD per kHz of additional error is to be added for frequencies > 20 kHz and signal inputs < 10% of range.
- U1273AX only: For all AC voltage ranges, the accuracy is specified at 2.5% + 25 counts when measuring below –20 °C for 20 to 45 Hz AC signals.

2. Notes for current specifications:

- Overload protection for 300 µA to 300 mA range: 0.44 A/1000 V; 10 × 35 mm 30 kA fast-acting fuse.
- Overload protection for 3 A to 10 A range: 11 A/1000 V; 10 × 38 mm 30 kA fast-acting fuse.
- Specification for 300 mA range: 440 mA continuous.
- Specification for 10 A range: 10 A continuous. Add 0.3% to the specified accuracy when measuring signals > 10 to 20 A for 30 seconds maximum. After measuring currents > 10 A, cool down the multimeter for twice the duration of the measured time before proceeding with low current measurements.
- U1273AX only: The accuracy for the 300 µA range, 3000 µA range, and 30 mA is specified after the Null function is used when measuring at temperatures below –20 °C. The Null function is used to subtract the test lead resistance and thermal effect (by shorting the test leads).
- U1273AX only: For all AC current ranges, the accuracy is specified at 2.5% + 25 counts when measuring below –20 °C for 20 to 45 Hz AC signals.

# AC + DC specifications for U1272A/U1273A and U1273AX

Accuracy  $\pm$  (% of reading + counts of least significant digit)

Function	Range	Resolution	45 Hz to 65 Hz	20 Hz to 1 kHz	1 kHz to 5 kHz	5 kHz to 20 kHz	20 kHz to 100 kHz
True RMS AC + DC voltage <sup>1</sup>	30 mV	0.001 mV	0.7 + 40	0.8 + 45	1.1 + 45	1.1 + 60	3.6 + 60
	300 mV	0.01 mV	0.7 + 25	0.8 + 30	1.1 + 30	1.1 + 45	3.6 + 45
	3 V	0.0001 V	0.7 + 25	1.1 + 30	1.6 + 30	2.1 + 45	3.6 + 45
	30 V	0.001 V	0.7 + 25	1.1 + 30	1.6 + 30	2.1 + 45	3.6 + 45
	300 V	0.01 V	0.7 + 25	1.1 + 30	1.6 + 30	2.1 + 45	—
	1000 V	0.1 V	0.7 + 25	1.1 + 30	1.6 + 30	—	—

Accuracy  $\pm$  (% of reading + counts of least significant digit)

Function	Range	Resolution	45 Hz to 65 Hz	20 Hz to 2 kHz	Burden voltage/Shunt
True RMS AC + DC current <sup>2</sup>	300 $\mu$ A	0.01 $\mu$ A	0.8 + 30	1.1 + 30	< 0.04 V/100 $\Omega$
	3000 $\mu$ A	0.1 $\mu$ A	0.8 + 30	1.1 + 30	< 0.4 V/100 $\Omega$
	30 mA	0.001 mA	0.8 + 30	1.1 + 30	< 0.08 V/1 $\Omega$
	300 mA	0.01 mA	0.8 + 30	1.1 + 30	< 1.00 V/1 $\Omega$
	3 A	0.0001 A	0.9 + 35	1.3 + 35	< 0.1 V/0.01 $\Omega$
	10 A	0.001 A	0.9 + 35	1.3 + 35	< 0.3 V/0.01 $\Omega$

- Notes for voltage specifications:
  - Overload protection: 1000 Vrms. For millivolt measurements, 1000 Vrms for short circuits with < 0.3 A current.
  - Input impedance: 10 M $\Omega$  (nominal) in parallel with < 100 pF.
  - The input signal is lower than the product of 20,000,000 V $\times$ Hz.
  - For 20 to 100 kHz accuracy: Three counts of the LSD per kHz of additional error is to be added for frequencies > 20 kHz and signal inputs < 10% of range.
  - U1273AX only: For all AC voltage ranges, the accuracy is specified at 2.5% + 25 counts when measuring below  $-20^{\circ}\text{C}$  for 20 to 45 Hz AC signals.
- Notes for current specifications:
  - Overload protection for 300  $\mu$ A to 300 mA range: 0.44 A/1000 V; 10  $\times$  35 mm 30 kA fast-acting fuse.
  - Overload protection for 3 A to 10 A range: 11 A/1000 V; 10  $\times$  38 mm 30 kA fast-acting fuse.
  - Specification for 300 mA range: 440 mA continuous.
  - Specification for 10 A range: 10 A continuous. Add 0.3% to the specified accuracy when measuring signals > 10 to 20 A for 30 seconds maximum. After measuring currents > 10 A, cool down the multimeter for twice the duration of the measured time before proceeding with low current measurements.
  - U1273AX only: The accuracy for the 300  $\mu$ A range, 3000  $\mu$ A range, and 30 mA is specified after the Null function is used when measuring at temperatures below  $-20^{\circ}\text{C}$ . The Null function is used to subtract the test lead resistance and thermal effect (by shorting the test leads).
  - U1273AX only: For all AC current ranges, the accuracy is specified at 2.5% + 25 counts when measuring below  $-20^{\circ}\text{C}$  for 20 to 45 Hz AC signals.

## Temperature specifications <sup>1-4</sup>

Accuracy  $\pm$  (% of reading + as specified below)

Thermocouple type	Range	Resolution	U1271A	U1272A	U1273A/U1273AX
K	-200 to 1372 $^{\circ}\text{C}$	0.1 $^{\circ}\text{C}$	1% reading + 1 $^{\circ}\text{C}$	1% reading + 1 $^{\circ}\text{C}$	1% reading + 1 $^{\circ}\text{C}$
	-328 to 2502 $^{\circ}\text{F}$	0.1 $^{\circ}\text{F}$	1% reading + 1.8 $^{\circ}\text{F}$	1% reading + 1.8 $^{\circ}\text{F}$	1% reading + 1.8 $^{\circ}\text{F}$
J	-210 to 1200 $^{\circ}\text{C}$	0.1 $^{\circ}\text{C}$	—	1% reading + 1 $^{\circ}\text{C}$	1% reading + 1 $^{\circ}\text{C}$
	-346 to 2192 $^{\circ}\text{F}$	0.1 $^{\circ}\text{F}$	—	1% reading + 1.8 $^{\circ}\text{F}$	1% reading + 1.8 $^{\circ}\text{F}$

- The specifications above is specified after 60 minutes of warm-up time.
- The accuracy does not include the tolerance of the thermocouple probe.
- Do not allow the temperature sensor to contact a surface that is energized above 30 Vrms or 60 V DC. Such voltages pose a shock hazard.
- The temperature calculation is specified according to the safety standards of EN/IEC-60548-1 and NIST175.

## Capacitance specifications <sup>5, 6</sup>

Accuracy $\pm$ (% of reading + counts of least significant digit)				
Range	Resolution	U1271A	U1272A	U1273A/U1273AX
10 nF	0.001 nF	1 + 5	1 + 5	1 + 5
100 nF	0.01 nF	1 + 2	1 + 2	1 + 2
1000 nF	0.1 nF	1 + 2	1 + 2	1 + 2
10 $\mu$ F	0.001 $\mu$ F	1 + 2	1 + 2	1 + 2
100 $\mu$ F	0.01 $\mu$ F	1 + 2	1 + 2	1 + 2
1000 $\mu$ F	0.1 $\mu$ F	1 + 2	1 + 2	1 + 2
10 mF	0.001 mF	1 + 2	1 + 2	1 + 2

5. Overload protection: 1000 Vrms for short circuits with  $< 0.3$  A current.

6. The accuracy for all ranges is specified based on a film capacitor or better, and after the Null function is used to subtract the test lead resistance and thermal effect (by opening the test leads).

## Frequency specifications <sup>1, 2</sup>

Range	Resolution	Accuracy $\pm$ (% of reading + counts of least significant digit)	Maximum input frequency
99.999 Hz	0.001 Hz	0.02 + 5	0.5 Hz
999.99 Hz	0.01 Hz	0.005 + 5	
9.9999 kHz	0.1 Hz	0.005 + 5	
99.999 kHz	1 Hz	0.005 + 5	
999.99 kHz	0.01 Hz	0.005 + 5	
> 1 MHz	0.1 Hz	0.005 + 5 @ $< 1$ MHz	

1. Overload protection: 1000 V; input signal is  $< 20,000,000$  V  $\times$  Hz (product of voltage and frequency).

2. The frequency measurement is susceptible to error when measuring low-voltage, low-frequency signals. Shielding inputs from external noise pickup is critical for minimizing measurement errors. Turning on the low pass filter may help you to filter out the noise and achieve a stable reading.

## Duty cycle <sup>3</sup>

Mode	Range	Accuracy at full scale
DC coupling	99.99%	0.3 % per kHz + 0.3 %
AC coupling	99.99%	0.3 % per kHz + 0.3 %

3. Notes for duty cycle specifications:

- The accuracy for duty cycle and pulse width measurements is based on a 3 V square wave input to the DC 3 V range. For AC couplings, the duty cycle range can be measured within the range of 10% to 90% for signal frequencies  $> 20$  Hz.
- The range of the duty cycle is determined by the frequency of the signal:  $\{10 \mu\text{s} \times \text{frequency} \times 100\%\}$  to  $\{[1 - (10 \mu\text{s} \times \text{frequency})] \times 100\%\}$ .
- The pulse width (positive or negative) must be  $> 10 \mu\text{s}$ . The range of the pulse width is determined by the frequency of the signal.

## Pulse width <sup>4</sup>

Range	Resolution	Accuracy at full scale
999.99 ms	0.01 ms	(duty cycle accuracy/frequency) + 0.01 ms
2000.0 ms	0.1 ms	(duty cycle accuracy/frequency) + 0.1 ms

4. Notes for pulse width specifications:

- The accuracy for duty cycle and pulse width measurements is based on a 3 V square wave input to the DC 3 V range.
- The pulse width (positive or negative) must be > 10  $\mu$ s. The range of the pulse width is determined by the frequency of the signal.

## U1271A and U1272A frequency sensitivity for voltage measurements <sup>1, 2, 3</sup>

Input range	Minimum sensitivity (RMS sine wave)			Trigger level for DC coupling 0.5 Hz to 200 kHz	
	15 Hz to 100 kHz	0.5 Hz to 200 kHz	Up to 1 MHz	U1271A	U1272A
30 mV	3 mV	3 mV	—	—	5 mV
300 mV	6 mV	8 mV	40 mV	10 mV	15 mV
3 V	0.12 V	0.2 V	0.4 V	0.15 V	0.15 V
30 V	0.6 V	0.8 V	2.6 V	1.5 V	1.5 V
300 V	6 V	8 V @ < 100 kHz	—	9 V @ < 100 kHz	9 V @ < 100 kHz
1000 V	50 V	50V@ < 100 kHz	—	90 V @ <100 kHz	90 V @ <100 kHz

1. Maximum input for specified accuracy, refer to “AC specifications” on page 11.

2. 30 mV range applicable for U1272A only.

3. 200 kHz to 1 MHz range applicable for U1272A only.

## U1273A/U1273AX sensitivity for voltage measurements <sup>4</sup>

Input range	Frequency sensitivity and trigger level			
Maximum input for specified accuracy, refer to AC voltage	Minimum sensitivity (RMS sine wave)			Trigger level for DC coupling
	15 Hz to 100 kHz	0.5 Hz to 200 kHz	Up to 1 MHz	0.5 Hz to 200 kHz
30 mV	3 mV	3 mV	—	5 mV
300 mV	7 mV	8 mV	38 mV	15 mV
3 V	0.12 V	0.2 V	0.48 V	0.15 V
30 V	0.8 V	0.8 V	3.5 V	1.5 V
300 V	6.7 V	8 V < 100 kHz	—	11 V < 100 kHz
1000 V	67 V	67 V < 100 kHz	—	110 V < 100 kHz

4. Maximum input for specified accuracy, refer to “AC specifications” on page 12.

## Frequency sensitivity for current measurements <sup>5</sup>

Minimum sensitivity (RMS sine wave) 2 Hz to 30 kHz

Input range	U1271A/U1272A	U1273A/U1273AX
300 $\mu$ A	100 $\mu$ A	70 $\mu$ A
3000 $\mu$ A	70 $\mu$ A	120 $\mu$ A
30 mA	1.2 mA	1.2 mA
300 mA	12 mA	12 mA
3 A	0.12 A	0.12 A
10 A	1.2 A	1.2 A

5. Maximum input for specified accuracy, refer to "AC specifications" on page 11 and 12.

## Peak hold

Signal width	Accuracy for DC voltage and current
Single event >1 ms	Specified accuracy + 400
Repetitive >250 $\mu$ s	Specified accuracy + 1000

## Decibel (dB) for U1272A and U1273A <sup>1, 2, 3</sup>

dB	Reference	Default reference
1 mW (dBm)	1 to 9999 $\Omega$	50 $\Omega$
1 V (dBV)	1 V	1 V

1. The reading of dBm is indicated in decibels of power above or below 1 mW, or decibels of voltage above or below 1 V. The formula is calculated according to the voltage measurement and specified reference impedance. Its accuracy is depended on the accuracy of the voltage measurement. See Decibel (dBV) accuracy table below.
2. Auto-ranging mode is used.
3. The bandwidth is according to voltage measurement.

## Decibel (dBV) accuracy

dBV range			Accuracy				
Range	Minimum	Maximum	45 Hz to 65 Hz	20 Hz to 1 kHz	45 Hz to 5 kHz	5 kHz to 20 kHz	20 kHz to 100 kHz
30 mV	-56.48	-30.46	0.06	0.07	0.09	0.1	0.32
300 mV	-36.48	-10.46	0.06	0.07	0.09	0.1	0.32
3 V	-16.48	+9.54	0.06	0.09	0.14	0.19	0.32
30 V	+3.52	+29.54	0.06	0.09	0.14	0.19	0.32
300 V	+23.52	+49.54	0.06	0.09	0.14	0.19	—
1000 V	+33.98	+60	0.06	0.09	0.14	—	—



## Measurement rate (approximate)

Function	Times / second	
	U1271A	U1272A/U1273A/U1273AX
ACV	7	7
DCV	7	7
$\Omega$	14	14
$\Omega$ with offset compensation	—	3
Diode	14	14
Auto diode	—	3
Capacitance	4 (< 100 $\mu$ F)	4 (< 100 $\mu$ F)
DCA	7	7
ACA	7	7
Temperature	7	7
Frequency	2 (> 10 Hz)	2 (> 10 Hz)
Duty cycle	1 (> 10 Hz)	1 (> 10 Hz)
Pulse width	1 (> 10 Hz)	1 (> 10 Hz)

# Ordering Information



U1271A



U1272A



U1273A



U1273AX

## Optional accessories

### Measuring accessories (non-temperature)



#### U1161A Extended test lead kit

Includes two test leads (red and black), two test probes, medium- sized alligator clips and 4-mm banana plugs.

- Test leads: CAT III 1000 V, CAT IV 600 V, 15 A
- Test probes (4-mm tips): CAT III 1000 V, CAT IV 600 V, 15 A
- Medium-sized alligator clips: CAT III 1000 V/CAT IV 600 V, 15 A
- 4-mm banana plugs: CAT II 600 V, 10 A



#### U1162A Alligator clips

- One pair of insulated alligator clips (red and black). Recommended for use with Keysight standard test leads.
- CAT III 1000 V, CAT IV 600 V, 15 A



#### U1163A SMT grabbers

- One pair of SMT grabbers (red and black). Recommended for use with Keysight standard test leads.
- Rated CAT II 300 V, 3 A



#### U1164A Fine-tip test probes

- One pair of fine-tip test probes (red and black). Recommended for use with Keysight standard test leads.
- Rated CAT II 300 V, 3 A



#### U1168A Standard test lead kit




Includes two test leads (red and black), 4-mm test probes, alligator clips, fine-tip test probes, SMT grabbers and mini grabber (black).

- Test leads: CAT III 1000 V, CAT IV 600 V, 15 A
- Test probe (19-mm tips): CAT II 1000 V, 15 A
- Test probe (4-mm tips): CAT III 1000 V, CAT IV 600 V, 15 A (highly recommended for CAT IV environment)
- Alligator clips: CAT III 1000 V, CAT IV 600 V, 15 A
- Fine-tip test probes: CAT II 300 V, 3 A
- SMT grabber: CAT II 300 V, 3 A
- Mini grabber: CAT II 300 V, 3 A

## Measuring accessories (non-temperature)

	<p><b>U1180A Thermocouple adapter + lead kit, J and K types</b></p> <ul style="list-style-type: none"> <li>• Includes thermocouple adapter, thermocouple bead J-type and thermocouple bead K-type.</li> <li>• T/C adapter J/K-type</li> <li>• T/C bead J-type: –20 to 200 °C</li> <li>• T/C bead K-type: –20 to 200 °C</li> </ul>
	<p><b>U1181A Immersion temperature probe</b></p> <ul style="list-style-type: none"> <li>• Type-K T/C for use in oil and other liquids</li> <li>• Measurement range: –50 to 700 °C</li> <li>• Includes adapter U1184A for connection to DMM</li> </ul>
	<p><b>U1182A Industrial surface temperature probe</b></p> <ul style="list-style-type: none"> <li>• Type-K T/C for use on still surfaces</li> <li>• Measurement range: –50 to 400 °C</li> <li>• Includes adapter U1184A for connection to DMM</li> </ul>
	<p><b>U1183A Air temperature probe</b></p> <ul style="list-style-type: none"> <li>• Type-K T/C for use in air and non-caustic gas</li> <li>• Measurement range: –50 to 800 °C</li> <li>• Includes adapter U1184A for connection to DMM</li> </ul>
	<p><b>U1184A Temperature probe adapter</b></p> <ul style="list-style-type: none"> <li>• Mini-connector-to-banana-plug adapter for use with DMM</li> </ul>
	<p><b>U1185A J-type thermocouple and adapter</b></p> <ul style="list-style-type: none"> <li>• T/C adapter J/K-type</li> <li>• T/C bead J-type: –20 to 200 °C</li> </ul>
	<p><b>U1186A K-type thermocouple and adapter</b></p> <ul style="list-style-type: none"> <li>• T/C adapter J/K-type</li> <li>• T/C bead J-type: –20 to 200 °C</li> </ul>

## Measuring accessories (non-temperature)

	<p><b>U1171A Magnetic hanging kit</b></p> <ul style="list-style-type: none"><li>• For fastening the DMM to a steel surface so both hands are free</li></ul>
	<p><b>U1173B IR-to-USB cable</b></p> <ul style="list-style-type: none"><li>• For remote control and data logging to PC</li><li>• Maximum baud rate: 19,200 bits per second</li></ul>
	<p><b>U1174A Soft carrying case</b></p> <ul style="list-style-type: none"><li>• The convenient way to carry your DMM and essential accessories</li><li>• – Dimension: 9 inches (H) x 5 inches (W) x 3 inches (D)</li></ul>

**dataTec**

Mess- und Prüftechnik. Die Experten.

**Ihr Ansprechpartner /  
Your Partner:**

**dataTec AG**

E-Mail: [info@datatec.eu](mailto:info@datatec.eu)

>>> [www.datatec.eu](http://www.datatec.eu)

 **KEYSIGHT**  
Authorized Premium  
Distributor

Keysight enables innovators to push the boundaries of engineering by quickly solving design, emulation, and test challenges to create the best product experiences. Start your innovation journey at [www.keysight.com](http://www.keysight.com).

This information is subject to change without notice. © Keysight Technologies, 2017 – 2025,  
Published in USA, July 25, 2025, 5990-6425EN